

High Voltage Electrical Installations | SAFE WORK METHOD STATEMENT (SWMS)

TASK OR ACTIVITY: High Voltage Electrical Installations

Business Name: [Company Name]

ABN: [ABN]

SWMS#

Business Address: [Company Address]

Contact Person:

Phone: [Phone]

Email:

THIS SAFE WORK METHOD STATEMENT IS APPROVED BY THE PCBU OF THE PROJECT

Under the Work Health and Safety Regulation (WHS Regulation), a person conducting a business or undertaking (PCBU) is required to ensure that a safe work method statement (SWMS) is prepared before the proposed work starts.

Full Name:

Signature:

Title:

Date:

Details of the person(s) responsible for ensuring implementation, monitoring and compliance of the SWMS, as well as reviews and modifications of the SWMS.

Full Name:

Title:

Phone:

ALL PERSONNEL PARTICIPATING IN ANY ACTIVITY ON THIS SWMS MUST HAVE THE FOLLOWING COMMUNICATED

NAME AND DATED SIGNATURE OF ALL RELEVANT PERSONNEL WHO HAVE BEEN CONSULTED AND COMMUNICATED TO IN THE DEVELOPMENT AND APPROVAL OF THIS SWMS

Safety meetings or toolbox talks will be scheduled in accordance with legislative requirements to first identify any site hazards, secondly to communicate those hazards and then to further take steps to either eliminate or control each hazard.

NAME

SIGNATURE

DATE

If an incident or a near miss occurs, all work must stop immediately. Depending on the severity of the incident, a meeting will be called with all workers to amend the SWMS if required. The meeting may also be an educational opportunity.

Any changes made to the SWMS after an incident or a near miss must be approved by the Person Conducting Business or Undertaking and communicated to all relevant personnel.

The SWMS must be kept and be available for inspection at least until the work is completed. Where a SWMS is revised, all versions should be kept. If a notifiable incident occurs in relation to which the SWMS relates, then the SWMS must be kept for at least two years from the occurrence of the notifiable incident.

CLIENT OR PRINCIPAL CONTRACTOR DETAILS

Client:	SCOPE OF WORKS Provide a detailed description of the specific work being carried out (otherwise known as a scope of works).
Project Name:	
Project Address:	
Project Manager:	
Contact Phone:	
Project Manager Signature:	
Date SWMS supplied to Project Manager:	

ANY HIGH-RISK CONSTRUCTION WORK BEING CARRIED OUT

☐ involves a risk of a person falling more than 2 meters.	☐ is carried out on or near pressurised gas mains or piping.
☐ is carried out on a telecommunication tower.	☐ is carried out on or near chemical, fuel or refrigerant lines.
☐ involves demolition of an element of a structure that is load-bearing.	☐ is carried out on or near energised electrical installations or services.
☐ involves demolition of an element related to the physical integrity of a structure.	☐ is carried out in an area that may have a contaminated or flammable atmosphere.
☐ involves, or is likely to involve, disturbing asbestos.	☐ involves tilt-up or precast concrete.
☐ involves structural alteration or repair that requires temporary support to prevent collapse.	☐ is carried out on, in or adjacent to a road, railway, shipping lane or other traffic corridor.
☐ is carried out in or near a confined space.	☐ is carried out in an area of a workplace where there is any movement of powered mobile plant.
☐ is carried out in/near a shaft or trench deeper than 1.5m or tunnel involving use of explosives.	☐ is carried out in areas with artificial extremes of temperature.
☐ is carried out in or near water or other liquid that involves a risk of drowning.	☐ involves diving work.

ANY HIGH-RISK MACHINERY OR EQUIPMENT NEARBY

☐ Forklift	☐ Crane/s	☐ Hoist/s	☐ Excavator	☐ Backhoe/Loader	☐ Boom Lift	☐ EWP	☐ Genie Lift
☐ Trencher	☐ Drilling Rig	☐ Trucks	☐ Formwork	☐ Bobcat	☐ Flammable Gas	☐ Fuel	☐ Dozer
☐ High Voltage	☐ Mulcher	☐ Tilt-up Panels	☐ Roller	☐ Scissor Lift	☐ Tractor	☐ Other -	

RISK MATRIX

LIKELIHOOD	INSIGNIFICANT	MINOR	MODERATE	MAJOR	CATASTROPHIC	SCORE	ACTION	HEIRARCHY OF CONTROLS
ALMOST CERTAIN	3 HIGH	3 HIGH	4 ACUTE	4 ACUTE	4 ACUTE			Elimination Remove the hazard.
LIKELY	2 MODERATE	3 HIGH	3 HIGH	4 ACUTE	4 ACUTE	4A ACUTE	DO NOT PROCEED	Substitution Replace the hazard.
POSSIBLE	1 LOW	2 MODERATE	3 HIGH	4 ACUTE	4 ACUTE	3H HIGH	Review before work starts.	Isolation Isolate People from the hazard
UNLIKELY	1 LOW	1 LOW	2 MODERATE	3 HIGH	4 ACUTE	2M MODERATE	Ensure control measures in place.	Engineering Isolate the hazard.
RARE	1 LOW	1 LOW	2 MODERATE	3 HIGH	3 HIGH	1L LOW	Monitor and keep records	Administrative Change the work. PPE

Notes on Hierarchy of Controls: Elimination methods are the most effective and preferred when controlling a hazard. Substitution is the second most effective method of controlling a hazard. Engineering by isolation is the third most effective, while Administrative Controls by changing the work is the fourth most effective method. PPE (Personal Protective Equipment) is the least effective method.

PERSONAL PROTECTIVE EQUIPMENT (PPE)

FOOT PROTECTION	HAND PROTECTION	HEAD PROTECTION	HEARING PROTECTION	EYE PROTECTION	RESPIRATORY PROTECTION	FACE PROTECTION	HIGH-VIS CLOTHING	PROTECTIVE CLOTHING	FALL PROTECTION	SUN PROTECTION	HAIR/JEWELLERY SECURED
											
☐	☐	☐	☐	☐	☐	☐	☐	☐	☐	☐	☐

Select the appropriate PPE above suitable for the equipment used or the job task being performed (if applicable).

Note: A SWMS must be reviewed regularly to make sure it remains effective. A SWMS must be reviewed (and revised if necessary) if relevant control measures are revised. The review process should be carried out in consultation with workers (including contractors and subcontractors) who may be affected by the operation of the SWMS and their health and safety representatives who represented that work group at the workplace.

When a SWMS has been revised, the person conducting a business or undertaking must ensure all:

1. persons involved in the work are advised that a revision has been made and how they can access the revised SWMS;
2. persons who will need to change a work procedure or system as a result of the review are advised of the changes in a way that will enable them to implement their duties consistently with the revised SWMS; and,
3. workers that will be involved in the work are provided with the relevant information and instruction that will assist them to understand and implement the revised SWMS.

JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR	RESPONSIBLE PERSON
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK	NAME OF PERSON
1. Preparation	Electrocution, Trip hazards	3H	- Conduct a thorough risk assessment: Prior to commencing high voltage electrical installation work, perform a detailed hazard identification and risk assessment to ensure all potential hazards are identified and control measures are implemented to mitigate the risks. - Establish safe work zones: Properly demarcate the work area with barrier tape, warning signs, or temporary fencing in accordance with Australian Standards, to prevent unauthorised access and reduce the risk of trip hazards caused by stray cables or equipment. - Implement Lockout/Tagout procedures: Implement the implemented isolation, lockout/tagout procedures to ensure that high voltage equipment is properly de-energised, isolated, and cannot be inadvertently re-energised by other personnel during work activities. - Use appropriate personal protective equipment (PPE): Ensure that workers wear necessary PPE, including insulated gloves, safety footwear, and eye protection, while carrying out tasks associated with high voltage installations to minimise the risk of injury due to electrocution or trip hazards. - Prioritise employee training: Ensure all employees have received relevant training and hold relevant certifications for working safely with high voltage installations, in line with Australian Standards and Workplace Health & Safety regulations. - Provide adequate supervision: Assign a designated competent and qualified supervisor to oversee the work, ensuring that safety procedures are followed, and any potential hazards are promptly addressed. - Regularly inspect tools and equipment: Before commencing the work step, inspect all tools, equipment, and machinery to ensure they are in proper working order and free from defects. Replace damaged or faulty items as needed. - Manage housekeeping: Maintain a clean and organised workspace to minimise trip hazards and the associated risks. Keep walkways and access paths clear of cords, cables, and any other obstructions. - Adopt proper manual handling techniques: Train staff to use correct lifting and carrying techniques, and provide appropriate aids such as trolleys or carts for moving heavy electrical components, minimising the risk of trip hazards and injury. - Develop emergency response plans: Implement a well-documented incident and emergency response plan outlining the procedures to follow in case of accidents involving high voltage electrical installations. Regularly review, update, and communicate this plan to all personnel on site.	2M	
2. Site assessment	Falling objects, Unqualified staff	3H	- Conduct thorough site inspections before commencing work to identify potential hazards such as unstable structures, obstacles, or trip hazards and take appropriate preventative measures. - Implement a barricading system around the work area to prevent unauthorised access and protect workers from potential falling objects or other hazards.	1L	

JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR	RESPONSIBLE PERSON
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK	NAME OF PERSON
			- Develop and enforce a traffic management plan for the movement of vehicles and heavy equipment within and around the worksite to minimise the risk of collisions or toppled loads. - Provide workers with appropriate Personal Protective Equipment (PPE) including safety helmets, high-visibility clothing, safety footwear, and gloves to minimise the risk of injury from falling objects or other hazards. - Designate 'no-go' areas within the work zone where only qualified and authorised personnel are allowed to enter, ensuring that unqualified staff are restricted from accessing hazardous zones. - Securely store tools and materials when not in use, implementing storage racks, restraints or barriers as necessary to prevent the possibility of falling objects, particularly at height. - Ensure all staff receive comprehensive training on the specific tasks they will carry out as part of the project as well as any additional site-specific safety requirements. - Regularly inspect, repair and maintain equipment and tools used for high voltage electrical installations, ensuring their safe operation throughout the project. - Establish clear lines of communication between team members, supervisors, and other relevant parties, utilising appropriate communication devices such as radios or hand signals to promote workplace safety. - Implement procedures for reporting and rectifying hazards or potential hazards, allowing for swift resolution and ongoing maintenance of a safer working environment. - Conduct regular toolbox talks and safety briefings to keep staff informed about work progress, changing conditions or new hazards, and reinforcing the importance of safety practices. - Continuously review and update the Safe Work Method Statement (SWMS) as necessary throughout the course of the project to ensure its accuracy, effectiveness, and adherence to current safety legislation and best practices.		
3. Isolation verification	Electrocution, Incomplete isolation	4A	- Ensure all necessary permits are obtained and displayed, such as Electrical Access Permits (EAPs) or Isolation Certificates, before commencing work. - Conduct a thorough risk assessment of the site, including identifying any potential hazards and implementing appropriate safety measures. - Follow established Lockout/Tagout (LOTO) procedures to ensure all energy sources are isolated and secured, using appropriate lockout devices and safety tags. - Utilise isolation and test equipment that conforms to Australian Standards, ensuring tools are in good working order and inspected regularly for defects. - Employ qualified personnel with requisite training and competencies in high voltage electrical installations, such as Electricians and Electrical Engineers, to undertake the isolation verification process.	2M	

JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR	RESPONSIBLE PERSON
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK	NAME OF PERSON
			- Verify correct identification of the specific electrical circuits and components requiring isolation, cross-checking against diagrams, schematics, and device labelling. - Confirm complete isolation of the supply by testing equipment and circuits using approved Voltage Detection Devices (VDDs) following safe work practices to prevent inadvertent contact with live conductors. - Implement a thorough communication plan and ensure all workers involved in the project, ensuring each individual understands their role, responsibilities, and response protocols in case of an emergency. - Keep a detailed log of isolation activities, including individual responsibilities and timeframes, ensuring a clear audit trail and assisting in tracking work progress. - Adopt a multiple-barriers approach during works when feasible, applying various safety measures to control risk exposure such as insulated barriers and warning signs. - Establish clearly defined 'No Go' zones around high voltage equipment, communicating these areas through on-site signage or physical barriers, ensuring access is restricted to authorised personnel. - Provide ongoing training and toolbox talks for staff, ensuring employees remain up-to-date with the latest best-practice guidelines and relevant legislation to maintain a high level of safety awareness. - Conduct regular inspections, audits, and reviews of isolation procedures and the wider workplace, to identify areas for improvement and continually raise safety standards in high voltage electrical installations.		
4. Install warning signs	Adverse weather, Poor visibility	2M	██ ██ ██ ██ ██	1L	

JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR	RESPONSIBLE PERSON
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK	NAME OF PERSON
			[REDACTED]		
			[REDACTED]		
			[REDACTED]		
			[REDACTED]		
			[REDACTED]		
			[REDACTED]		
			[REDACTED]		
			[REDACTED]		
			[REDACTED]		
			[REDACTED]		
5. Obtain permits	Invalid permits, Miscommunication	2M	[REDACTED]	1L	
			[REDACTED]		
			[REDACTED]		
			[REDACTED]		
			[REDACTED]		

SAMPLE

SAMPLE

SAMPLE

JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR	RESPONSIBLE PERSON
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK	NAME OF PERSON
9. Establish grounding	Improper grounding, Substandard materials	H		1L	

JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR	RESPONSIBLE PERSON
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK	NAME OF PERSON
10. Execute lockout/tagout	Unauthorised access, Incorrect procedures	3H		1L	

JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR	RESPONSIBLE PERSON
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK	NAME OF PERSON
11. Inspect switches and cables	Damaged cables, Switch malfunctions	3H		2M	

JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR	RESPONSIBLE PERSON
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK	NAME OF PERSON
			[REDACTED]		
			[REDACTED]		
			[REDACTED]		
			[REDACTED]		
12. Disconnect power sources	Inadequate lockout Human error	4A	[REDACTED]	2M	
			[REDACTED]		
			[REDACTED]		
			[REDACTED]		
			[REDACTED]		
			[REDACTED]		
			[REDACTED]		
			[REDACTED]		
			[REDACTED]		

JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR	RESPONSIBLE PERSON
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK	NAME OF PERSON
13. Conduct repairs/maintenance	Tool malfunctions, Unsafe work environment	3H		2M	

JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR	RESPONSIBLE PERSON
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK	NAME OF PERSON
14. Restore power	Electrical arcing, System faults	3H		2M	

JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR	RESPONSIBLE PERSON
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK	NAME OF PERSON
15. Incident reporting	Delayed reporting, Inaccurate information	2M		1L	

SAMPLE

JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR	RESPONSIBLE PERSON
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK	NAME OF PERSON
16. Clean up work area	Sharp objects, Hazardous substances	2M	SAMPLE	1L	

JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR	RESPONSIBLE PERSON
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK	NAME OF PERSON
17. Remove warning signs	Vandalism, Inattention	2M		1L	

JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR	RESPONSIBLE PERSON
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK	NAME OF PERSON
18. Decommissioning	Improper equipment handling, Electrical discharge	1SH		1L	

JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR	RESPONSIBLE PERSON
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK	NAME OF PERSON
19. Post-maintenance inspection	Faulty repairs, Missed hazards			1L	

JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR	RESPONSIBLE PERSON
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK	NAME OF PERSON
			[REDACTED]		
			[REDACTED]		
			[REDACTED]		
			[REDACTED]		
20. Documentation and review	Lost documents, Inadequate reviewing	2M	[REDACTED]	1L	
			[REDACTED]		
			[REDACTED]		
			[REDACTED]		
			[REDACTED]		
			[REDACTED]		

JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR	RESPONSIBLE PERSON
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK	NAME OF PERSON

EMERGENCY RESPONSE – CALL 000 FOR EMERGENCIES

Ensure to have an Emergency Management Plan in place as well as adequate numbers of trained first aid staff with easy access to fully stocked first aid kits, rescue equipment, material safety data sheets, adequate access to emergency communication equipment and fire-fighting equipment suitable for all classes of fire and ignition sources.

LEGISLATIVE REFERENCES

RELEVANT LEGISLATION AND CODES OF PRACTICE. DELETE THE LEGISLATIVE REFERENCES IF ANY STATE THAT ARE NOT APPLICABLE

Queensland & Australian Capital Territory

Work Health and Safety Act 2011

Work Health and Safety Regulations 2011

Legislation QLD: <https://www.worksafe.qld.gov.au/laws-and-compliance/work-health-and-safety-laws>

Codes of Practice QLD: <https://www.worksafe.qld.gov.au/laws-and-compliance/codes-of-practice>

Legislation ACT: <https://www.worksafe.act.gov.au/laws-and-compliance/acts-and-regulations>

Codes of Practice ACT: <https://www.worksafe.act.gov.au/laws-and-compliance/codes-of-practice>

Victoria

Occupational Health and Safety Act 2004

Occupational Health and Safety Regulations 2017

Legislation VIC: <https://www.worksafe.vic.gov.au/occupational-health-and-safety-act-and-regulations>

Codes of Practice VIC: <https://www.worksafe.vic.gov.au/compliance-codes-and-codes-practice>

New South Wales

Work Health and Safety Act 2011

Work Health and Safety Regulations 2017

Legislation NSW: <https://www.safework.nsw.gov.au/legal-obligations/legislation>

Codes of Practice NSW: <https://www.safework.nsw.gov.au/resource-library/list-codes-of-practice>

Western Australia

Work Health and Safety Act 2020

Work Health and Safety Regulations 2022

Legislation Western Australia: <https://www.commerce.wa.gov.au/worksafe/legislation>

Codes of Practice WA: <https://www.commerce.wa.gov.au/worksafe/codes-practice>

Northern Territory

Work Health and Safety (National Uniform Legislation) Act 2011

Work Health and Safety (National Uniform Legislation) Regulations 2011

Legislation NT: <https://worksafe.nt.gov.au/laws-and-compliance/workplace-safety/laws>

Codes of Practice NT: <https://worksafe.nt.gov.au/for-workplaces-and-resources/codes-of-practice>

Safe Work Australia Links

Law and Regulation (All States): <https://www.safeworkaustralia.gov.au/law-and-regulation>

Model Codes of Practice: <https://www.safeworkaustralia.gov.au/resources-publications/model-codes-of-practice>

Model Codes of Practice

- Managing noise and preventing hearing loss at work
- Confined spaces
- Labelling of workplace hazardous chemicals
- Managing risks of hazardous chemicals in the workplace
- Welding processes
- First aid in the workplace
- Managing the risk of falls at workplaces
- Hazardous manual tasks
- Managing the risk of falls in housing construction
- Managing electrical risks in the workplace
- Demolition work
- Excavation work
- Work health and safety consultation, cooperation and coordination
- Managing the work environment and facilities
- How to manage work health and safety risks
- Managing risks of plant in the workplace
- Construction work

South Australia

Work Health and Safety Act 2012 (SA)

Work Health and Safety Regulations 2012 (SA)

Legislation for SA: <https://www.safework.sa.gov.au/resources/legislation>

Codes of Practice for SA: <https://www.safework.sa.gov.au/workplaces/codes-of-practice#COPs>

Tasmania

Work Health and Safety Act 2012

Work Health and Safety (Transitional and Consequential Provisions) Act 2012

Work Health and Safety Regulations 2012

Work Health and Safety (Transitional) Regulations 2012

Legislation for TAS: <https://worksafe.tas.gov.au/topics/laws-and-compliance/acts-and-regulations>

Codes of Practice for TAS: <https://worksafe.tas.gov.au/topics/laws-and-compliance/codes-of-practice>

Details of permits, licenses or access required by regulatory bodies (add or delete as required):

- Permits from local council
- Authorisation to commence work
- Any required documents.

SIGNATORIES OF THE SAFE WORK METHOD STATEMENT

The signed and dated personnel listed below have cooperated in the consultation and development of this Safe Work Method Statement which has been approved by the Person/s Conducting a Business or Undertaking (PCBU). In signing this Safe Work Method Statement each individual acknowledges and confirms that they have read this SWMS in full, having raised any questions for items on this Safe Work Method Statement that require clarification, and confirms that they are competent, skilled and knowledgeable for the task assigned to them. Every person acknowledges that they have received the relevant training and qualifications where required, before carrying out any work contained in this Safe Work Method Statement. By signing this Safe Work Method Statement each individual agrees to work safely, to follow any safe work instructions which are provided, and agrees to use all Personal Protective Equipment where appropriate.

Worker Name	Position	Signature	Date	Time	Supervisor
			Date:		
			Date:		
			Date:		
			Date:		
			Date:		
			Date:		
			Date:		

SAFE WORK METHOD STATEMENT MONITORING AND REVIEW

The SWMS must be reviewed regularly to make sure it remains effective and must be reviewed (and revised if necessary) if relevant control measures are revised. The review process should be carried out in consultation with workers (including contractors and subcontractors) who may be affected by the operation of the SWMS and their health and safety representatives who represented that work group at the workplace.

When the SWMS has been revised the PCBU must ensure that all persons involved with the work are advised that a revision has been made and how they can access the revised SWMS, including all persons who will need to change a work procedure or system as a result of the review are advised of the changes in a way that will enable them to implement their duties consistently with the revised SWMS. All workers that will be involved in the work must be provided with the relevant information and instruction that will assist them to understand and implement the revised SWMS.

The SWMS must be monitored regularly for the effectiveness of ensuring hazard controls are effective in reducing the risk of incidents, keeping the workplace safe for all personnel. The person responsible for monitoring the effectiveness of the Safe Work Method Statement should employ a multi-faceted approach which includes but is not limited to:

1. Spot Checks.
2. Consultation with workers, contractors and sub-contractors.
3. Internal audits on a continual basis.

An approach of continuous improvement, promptly recording inconsistencies or deficiencies, followed up by immediate corrective action and consultation with all relevant personnel ensures that the PCBU is consistently developing ever-improving systems of safe work principles.

REVIEW NUMBER	☐ 1	☐ 2	☐ 3	☐ 4	☐ 5	☐ 6	☐ 7
NAME							
INITIALS							
DATE							

SAFE WORK METHOD STATEMENT REVIEW CHECKLIST

This Safe Work Method Statement Review Checklist is to be followed and used upon initial development of the SWMS to help ensure that all steps have been adequately taken before work commences. Think of this document as an internal audit review checklist before commencing work, and may form part of a Toolbox Talk (safety meeting) and may be used as an opportunity for education and training.

ITEMS WHICH MUST BE INCLUDED IN THE SWMS	COMPLETED	TO BE DONE	COMMENTS
The company details have been entered, including the project name and address.	☐	☐	
Names and signatures of all relevant personnel consulted during the development of the SWMS.	☐	☐	
Name, signature, position and date signed of the person approving the SWMS.	☐	☐	
Specific personnel and qualifications, experience is noted in the SWMS.	☐	☐	
Provides a step-by-step process of tasks required to carry out the activity or task.	☐	☐	
Adequate risk assessment of any identified hazards has been completed.	☐	☐	
Foreseeable hazards are identified and documented for each step.	☐	☐	
Any hazards listed in any site risk assessments have been added to the SWMS.	☐	☐	
SWMS initial risk (IR) column as well as residual risk (RR) columns completed.	☐	☐	
Check control measures added to the SWMS are the most effective solutions.	☐	☐	
Responsible person is assigned and listed on the SWMS for the implementation of control measures.	☐	☐	
Permit requirements specified, such as Hot Work, Electrical Work, Work at Heights etc.	☐	☐	
SWMS identifies plant and equipment to be used.	☐	☐	
Details of inspection checks required for any equipment listed are noted on the SWMS.	☐	☐	
Describes any mandatory qualifications, experience, training or skills required to perform the work.	☐	☐	
Applicable personal protective equipment is selected on the SWMS.	☐	☐	
Lists any required permits or licenses.	☐	☐	
Reflects and documents any legislative references and/or Australian Standards.	☐	☐	
Identifies any hazardous substances used with specific control measures in line with any SDS.	☐	☐	
REVIEWED BY		DATE REVIEWED	
SIGNATURE		DATE COMPLETED	