



### Carpet Maintenance Using Commercial Vacuum Cleaners | SAFE WORK METHOD STATEMENT (SWMS) TASK OR ACTIVITY: Carpet Maintenance Using Commercial Vacuum Cleaners **Business Name:** ABN: SWMS# Business Address: Contact Person: Phone: THIS SAFE WORK METHOD STATEMENT IS APPROVED BY THE PC. YOF THE PROJECT (PC\_1) is required to en that a safe work method statement (SWMS) is prepared before Under the Work Health and Safety Regulation (WHS Regulation), a person conducting a business or under the proposed work starts. Full Name: Title: Date: Signature: Details of the person(s) responsible for ensuring implementation, monitoring pliance VMS arrivell as reviews and modifications of the SWMS. Full Name: Title: Phone: ALL PERSONNEL PARTICIPATING IN ANY ACTIVITY ON THIS STIMS IN NA 2 OF ALL RELEVANT PERSONNEL WHO HAVE BEEN CONSULTED AND COMMUNICATED TO IN THE HAVE THE FOLLOWING COMMUNICATED EVELOPMENT AND APPROVAL OF THIS SWMS Safety meetings or toolbox talks will be sched and in according with gislative requirements to first identify any site hazards. nica those hazards and then to further take steps to either eliminate or conf each hazard. If an incident or a near miss occurs, all work must ste alately. Depending on the severity of the incident, a meeting will be called with all workers to amend the SWMS if required. The meeting may also be an educational opportunity. Any changes made to the SWMS after an incident or a near miss must be approved by the Person Conducting Business or Undertaking and communicated to all relevant personnel. The SWMS must be kept and be available for inspection at least until the work is completed. Where a SWMS is revised, all versions should be kept. If a notifiable incident occurs in relation to which the SWMS relates, then the SWMS must be kept for at least two years from the occurrence of the notifiable incident.





CLIENT OR PRINCIPAL	CONTRACTOR DETAILS
Client:	SCOPE OF WORKS
Project Name:	
Project Address:	
Project Manager:	
Contact Phone:	
Date SWMS supplied to Project Manager:	
ANY HIGH BIOK CONSTRUCTOR	NAME OF THE POLIT
ANY HIGH-RISK CONSTRUCTOR	N WC & BEIN C ARIED OUT
☐ involves a risk of a person falling more than 2 meters	is carried out on or near pressurised gas mains or piping
☐ is carried out on a telecommunication tower	carried out on or near chemical, fuel or refrigerant lines
☐ involves demolition of an element of a structure that is load-bearing	$\square$ is carried out on or near energised electrical installations or services
☐ involves demolition of an element related to the physical integral of a functure	☐ is carried out in an area that may have a contaminated or flammable atmosphere
☐ involves, or is likely to involve, disturbing asb	☐ involves tilt-up or precast concrete
☐ involves structural alteration or repair that —quires term — v sup —rt to prevent collapse	☐ is carried out on, in or adjacent to a road, railway, shipping lane or other traffic corridor
☐ is carried out in or near a confined space	☐ is carried out in an area of a workplace where there is any movement of powered mobile plant
☐ is carried out in/near a shaft or trench deeper that. tunnel involving use of explosives	☐ is carried out in areas with artificial extremes of temperature.
$\square$ is carried out in or near water or other liquid that involves a risk of drowning.	☐ involves diving work.
ANY HIGH-RISK MACHINER	Y OR EQUIPMENT NEARBY



RISK MATRIX											
LIKELIHOOD	INSIGNIFICANT	MINOR	MODERATE	MAJOR	CATASTROPHIC	SCORE	ACTION	HEI	RARCHY OF CONTROLS		
ALMOST CERTAIN	3 HIGH	3 HIGH	4 ACUTE	4 ACUTE	4 ACUTE	SCORE	ACTION		Elimination Remove the hazard.		
LIKELY	2 MODERATE	3 HIGH	3 HIGH	4 ACUTE	4 ACUTE	4A ACUTE	DO NOT PROCE		Substitution		
POSSIBLE	1 LOW	2 MODERATE	3 HIGH	4 ACUTE	4 ACUTE	3H HIGH	Review before work starts.		Replace the hazard.		
UNLIKELY	1 LOW	1 LOW	2 MODERATE	3 HIGH	4 ACUTE	2M MODERATE	Ensure control measures in place.	Isolate	e People from the hazard		
RARE	1 LOW	1 LOW	2 MODERATE	3 HIGH	3 HIGH	1L LOW	nitor and		Engineering Isolate the hazard.		
is the second m	rchy of Controls: ost effective metho nging the work is th	d of controlling a	hazard. Enginee	ering by isolati	on is the in ost e	en 'ive, while	rd. Substitution Administrative effective		Administrative Change the work.  PPE		

	PERS_VAL   TECTIVE EQUIPMENT (PPE)										
		Select the app	ropriate PPŁ	abo v uitab	cor the equi	pment used or	the job task	being perforr	ned (if applica	ıble).	
FOOT PROTECTION	HAND PROTECTION	HEAD PROTECTION	HEARING ETION	P ECTION	PROTECTION	FACE PROTECTION	HIGH-VIS CLOTHING	PROTECTIVE CLOTHING	FALL PROTECTION	SUN PROTECTION	HAIR/JEWELLERY SECURED
Other PPE R	equired:										
	Pe	ermit or Licen	ses Requirem	ents			Ma	andatory Qual	ifications and	Training	



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
1. Preparation	Electrocution, Tripping over cords	2M	<ul> <li>Ensure all vacuum cleaners have a current pectrical safety test tag in compliance with AS/NZS 3760.</li> <li>Use commercial vacuum cleaners equippe with automatic shut-off switches to prevent overheating and electrical faults.</li> <li>Inspect electrical cords regionly for any signs or amage, froug, or wear before use.</li> <li>Equip workers with non-slip to ever to minimise the property of tripping over cords.</li> <li>Position cords may from ligh transpareas or secure them using cord covers to reduce tripping hazards.</li> <li>Develop a trait work are suyout property that pecifies safe passageways and designated cord routes.</li> <li>Trait employers on second management techniques, including looping or hanging excess cord length off them.</li> <li>Utilist coloress or potery-operated vacuum models where feasible to eliminate cord-related risks.</li> <li>Inform taff a put the poation and procedure for using circuit breakers and emergency stops in case of loctrical hoide.</li> <li>Respect maintain and inspect vacuum equipment to ensure it meets operational safety standards.</li> </ul>	1L
2. Inspecting Vacuum Cleaner	Electric Shock, Injury from damaged equipment	ЗН	<ul> <li>sure power cords and plugs are intact and free from damage before use.</li> <li>Conduct a visual inspection of the vacuum cleaner for any signs of wear or damage.</li> <li>Test the functionality of all safety features, such as emergency shut-off switches, before operating the equipment.</li> <li>Verify that the vacuum cleaner's casing and housing are not cracked or damaged.</li> <li>Confirm that all warning labels and safety instructions on the equipment are clearly visible and legible.</li> <li>Ensure that the electrical components have been tested and tagged by a licensed electrician within the specified timeframe.</li> <li>Remove the vacuum cleaner from service immediately if any defects or faults are identified.</li> <li>Use only manufacturer-approved extension cords and ensure they are fully unwound to prevent overheating.</li> <li>Keep power cords and cables away from water sources and high-traffic areas to minimise tripping hazards.</li> <li>Train staff in correctly identifying equipment damage and reporting procedures.</li> <li>Store vacuum cleaners in a designated area away from potential hazards like moisture or heat when not in use.</li> <li>Schedule regular maintenance checks and servicing as per manufacturer guidelines to maintain equipment integrity.</li> </ul>	2M



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS  - Encourage workers to report any unusual sounds or performance issues with the equipment while in use.  - Implement a tagging system for operational readings, indicating whether equipment is ready to use, under maintenance, or requires repair.	RESIDUAL RISK
3.Plugging In	Electric Shock, Tripping over cords	2M	<ul> <li>Ensure all electrical equipment is tested any agged scording to the current safety standards before use.</li> <li>Use vacuum cleaners that to double-insulated shave a residual current device (RCD) for additional protection against electric shoc.</li> <li>Inspect the power share of plug or any visible damage or wear before each use; do not use equipment with damaged or use or plug.</li> <li>Keep power ords away or water share and wet areas to prevent the risk of electric shock.</li> <li>Arrange cords of the do not cross walkways or create trip hazards; use cable covers if necessary to protect be use in high raffic areas.</li> <li>Unwire any traighter cords fully to prevent overheating and potential fire hazards caused by coiled or twisted ords.</li> <li>To GF 1 (Ground Fault Circuit Interrupter) protected outlets, especially in older buildings where RCDs may, or by installed.</li> <li>Blan the vayout of work to minimise cord lengths required, reducing the potential for tripping incidents.</li> <li>Incelement clear signage and barriers to alert others on the premises about cord positions to reduce tripping hazards.</li> <li>Train workers on the importance of maintaining awareness of their surroundings and regularly repositioning cords out of pathways during use.</li> </ul>	1L
4. Testing Vacuum Cleaner	Noise, Electrocution	2M		1L



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
				•
5. Vacuuming	Back injuries, Tripro g over cords	ЗН		2M
				_
. Emptying Dust Bag	Exposure to Dust, Cuts	2M		1L



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
7. Dismantling for Cleaning	Injury from sharp parts, Back Strain	2M		1L



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
8. Internal Parts Exposure	Cutting finger, Inh. ation of duct	3H		2M
9. Assemble after Cleaning	Injury from sharp parts, Incorrect assembling	2M		1L



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
10. Checking Cords and Plugs	Electric Shock, Damaged cords	3Н		1L



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
11. Storing Vacuum Cleaner	Tripping over implemently stored the suum	2M		1L
12. Filing Faulty Equipment Form	Incorrect Data Entry, Stress related issues	1L		1L



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
13. Disconnecting Power Source	Electrical Shock, Damaged Cords	ЗН		2M
14. Wrapping Cords	Cord entanglement, Damaged Cords	2M		1L



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
15. Transporting Vacuum	Injury due to improper lifting, Tripping	2M		1L



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
16. Sanitising Work Equipment	Exposure to chemicals, Allergic Reaction	2M		1L
17. Packaging Vacuum for Transportation	Back strain from lifting, Damage to equipment	3Н		2M



POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
			•
Incorrect Data Entry, Streams	1L		1L
	Incorrect Data Entry, Stre	HAZARDS THAT MAY ARISE  INITIAL RISK  Incorrect Data Entry, Street	HAZARDS THAT MAY ARISE  INITIAL RISK  SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
19. Routine Equipment Check	Missing Faults, Incorrect usage of device	ЗН		2M
20. Decommissioning Old Vacuum Cleaners	Handling Heavy scraps, Exposure to dust	ЗН		2M



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK



#### **EMERGENCY RESPONSE - CALL 000 FOR EMERGENCIES**

Ensure to have an Emergency Management Plan in place as well as adequate numbers of trained first aid staff with easy access to fully stocked first aid kits, rescue equipment, material safety data sheets, adequate access to emergency communication equipment and fire-fighting equipment suitable for all classes of fire and ignition sources.

#### LEGISLATIVE REFERENCES

RELEVANT LEGISLATION AND CODES OF PRACTICE. DELETE THE LEGISLATIVE REFERENCES. ANY STATE AT ARE NOT APPLICABLE.

#### **Queensland & Australian Capital Territory**

Work Health and Safety Act 2011

Work Health and Safety Regulations 2011

Legislation QLD: https://www.worksafe.qld.gov.au/laws-and-compliance/work-health-and-safety-laws

Codes of Practice QLD: https://www.worksafe.qld.gov.au/laws-and-compliance/codes-of-practice Legislation ACT: https://www.worksafe.act.gov.au/laws-and-compliance/acts-and-regulations

Codes of Practice ACT: https://www.worksafe.act.gov.au/laws-and-compliance/codes-of-practice

#### **New South Wales**

Work Health and Safety Act 2011

Work Health and Safety Regulations 2017

Legislation NSW: https://www.safework.nsw.gov.au/legal-obligations/legislative

Codes of Practice NSW: https://www.safework.nsw.gov.au/resource-library/lis > odes-oi racti

#### **Northern Territory**

Work Health and Safety (National Uniform Legislation) Act 2011

Work Health and Safety (National Uniform Legislation) Regulation 201

Legislation NT: https://worksafe.nt.gov.au/laws-and-compliance/wo\_place-

Codes of Practice NT: https://worksafe.nt.gov.au/f

#### South Australia

Work Health and Safety Act 2012 (SA)

Work Health and Safety Regulations 2012 (SA)

Legislation for SA: https://www.safework.sa.gov.au/resources/le\_lation

Codes of Practice for SA: https://www.safework.sa.gov.au/work\_aces/codes-of-practice#COPs

#### Tasmania

Work Health and Safety Act 2012

Work Health and Safety (Transitional and Consequential Provisions) Act 2012

Work Health and Safety Regulations 2012

Work Health and Safety (Transitional) Regulations 2012

Legislation for TAS: https://worksafe.tas.gov.au/topics/laws-and-compliance/acts-and-regulations

Codes of Practice for TAS: https://worksafe.tas.gov.au/topics/laws-and-compliance/codes-of-practice

Details of permits, licenses or access required by regulatory bodies (add or delete as required):

- Permits from local council
- Authorisation to commence work
- Any required documents.

#### Victoria

Occupational Health al. Safety Act

Occupational Health and affety gulations 2017

Legis on VIC: https://www.csafe.vic.gov.au/occupational-health-and-safety-act-and-

gulat

des on actice VI autros://www.worksafe.vic.gov.au/compliance-codes-and-codes-practice

#### Western Australia

Work Health and Safety Act 2020

Work Health and Safety Regulations 2022

Legislation Western Australia: https://www.commerce.wa.gov.au/worksafe/legislation

Codes of Practice WA: https://www.commerce.wa.gov.au/worksafe/codes-practice

#### Safe Work Australia Links

Law and Regulation (All States): https://www.safeworkaustralia.gov.au/law-and-regulation Model Codes of Practice: https://www.safeworkaustralia.gov.au/resources-publications/model-codes-of-practice

#### **Model Codes of Practice**

- Managing noise and preventing hearing loss at work
- Confined spaces
- Labelling of workplace hazardous chemicals
- Managing risks of hazardous chemicals in the workplace
- Welding processes
- First aid in the workplace
- Managing the risk of falls at workplaces
- Hazardous manual tasks
- Managing the risk of falls in housing construction
- Managing electrical risks in the workplace
- Demolition work
- Excavation work
- Work health and safety consultation, cooperation and coordination
- Managing the work environment and facilities
- How to manage work health and safety risks
- Managing risks of plant in the workplace
- Construction work





### SIGNATORIES OF THE SAFE WORK METHOD STATEMENT

The signed and dated personnel listed below have cooperated in the consultation and development of this Safe Work Method Statement which has been approved by the Person/s Conducting a Business or Undertaking (PCBU). In signing this Safe Work Method Statement each individual acknowledges and confirms that they have read this SWMS in full, having raised any questions for items on this Safe Work Method Statement that require clarification, and confirms that they are competent, skilled and knowledgeable for the task assigned to them. Every person acknowledges that they have received the relevant training and qualifications where required, before carrying out any work contained in this Safe Work Method Statement. By signing this Safe Work Method Statement each individual agrees to work safely, to follow any safe work instructions which are provided, and agrees to use all Personal Protective Equipment where appropriate.

Worker Name	Signature	Date

#### SAFE WORK IN THE STATEMENT MONITORING AND REVIEW

The SWMS must be reviewed regularly to make sure it remains a fective of must be reviewed (and revised if necessary) if relevant control measures are revised. The view process should be carried out in consultation with workers (including contractors of the SWMS and their health and safety representatives who represented that work group at the workplace.

When the SWMS has been revised the PCBU mast ensure that advised that a revision has been made and how they can access the revised SWMS, including all persons who will need to change a work procedure or system as a rest of the review are advised of the changes in a way that will enable them to implement their duties and the involved in the work must be provided with the relevant information and instruction that will assist them to understand and implement the revised SWMS.

The SWMS must be monitored regularly for the effectiveness of ensuring hazard controls are effective in reducing the risk of incidents, keeping the workplace safe for all personnel. The person responsible for monitoring the effectiveness of the Safe Work Method Statement should employ a multi-faceted approach which includes but is not limited to:

- Spot Checks.
- 2. Consultation with workers, contractors and sub-contractors.
- 3. Internal audits on a continual basis.

An approach of continuous improvement, promptly recording inconsistencies or deficiencies, followed up by immediate corrective action and consultation with all relevant personnel ensures that the PCBU is consistently developing ever-improving systems of safe work principles.

REVIEW NUMBER	1	2	3	4	5	6	7
NAME							
INITIALS							
DATE							





### SAFE WORK METHOD STATEMENT REVIEW CHECKLIST

This Safe Work Method Statement Review Checklist is to be followed and used upon initial development of the SWMS to help ensure that all steps have been adequately taken before work commences. Think of this document as an internal audit review checklist before commencing work, and may form part of a Toolbox Talk (safety meeting) and may be used as an opportunity for education and training.

ITEMS WHICH MUST BE INCLUDED IN THE SWMS	COMPLETED	COMMENTS
The company details have been entered, including the project name and address.		
All relevant personnel consulted during the development of the SWMS.		
Name, signature, position and date signed of the person approving the SWMS.		
Specific personnel and qualifications, experience is noted in the SWMS.	7	
Provides a step-by-step process of tasks required to carry out the activity or task.		
Adequate risk assessment of any identified hazards has been completed.		
Foreseeable hazards are identified and documented for each step.		
Any hazards listed in any site risk assessments have been added to the SWMS		
SWMS initial risk (IR) column as well as residual risk (RR) column pleted.		
Check control measures added to the SWMS are the most effective selections		
Responsible person is assigned and listed on the part the important control measures.		
Permit or licenses requirements specified, sur as Hot Work, Electric Work, Work at Heights etc.		
SWMS identifies plant and equipment to be us		
Details of inspection checks required for any equipment listed an inoted on the SWMS.		
Describes any mandatory qualifications, experience, and or skills required to perform the work.		
Applicable personal protective equipment is selected on the SWMS.		
Reflects and documents any legislative references and/or Australian Standards.		
Identifies any hazardous substances used with specific control measures in line with any SDS.		
REVIEWED BY	DATE REVIEWE	D
SIGNATURE	DATE COMPLET	ED