

Electrical Maintenance, Fault Finding and Renovations | SAFE WORK METHOD STATEMENT (SWMS)

TASK OR ACTIVITY: Electrical Maintenance, Fault Finding and Renovations

Business Name:	ABN:	SWMS#
Business Address:		
Contact Person:	Phone:	Email:

THIS SAFE WORK METHOD STATEMENT IS APPROVED BY THE PCBU OF THE PROJECT

Under the Work Health and Safety Regulation (WHS Regulation), a person conducting a business or undertaking (PCBU) is required to ensure that a safe work method statement (SWMS) is prepared before the proposed work starts.

Full Name:		
Signature:	Title:	Date:
Details of the person(s) responsible for ensuring implementation, monitoring compliance of the SWMS as well as reviews and modifications of the SWMS.		
Full Name:	Title:	Phone:

ALL PERSONNEL PARTICIPATING IN ANY ACTIVITY ON THIS SWMS MUST HAVE THE FOLLOWING COMMUNICATED

Safety meetings or toolbox talks will be scheduled in accordance with legislative requirements to first identify any site hazards, then to communicate those hazards and then to further take steps to either eliminate or control each hazard.

If an incident or a near miss occurs, all work must stop immediately. Depending on the severity of the incident, a meeting will be called with all workers to amend the SWMS if required. The meeting may also be an educational opportunity.

Any changes made to the SWMS after an incident or a near miss must be approved by the Person Conducting Business or Undertaking and communicated to all relevant personnel.

The SWMS must be kept and be available for inspection at least until the work is completed. Where a SWMS is revised, all versions should be kept. If a notifiable incident occurs in relation to which the SWMS relates, then the SWMS must be kept for at least two years from the occurrence of the notifiable incident.

NAME OF ALL RELEVANT PERSONNEL WHO HAVE BEEN CONSULTED AND COMMUNICATED TO IN THE DEVELOPMENT AND APPROVAL OF THIS SWMS

CLIENT OR PRINCIPAL CONTRACTOR DETAILS

Client:	SCOPE OF WORKS
Project Name:	
Project Address:	
Project Manager:	
Contact Phone:	
Date SWMS supplied to Project Manager:	

ANY HIGH-RISK CONSTRUCTION WORK BEING CARRIED OUT

- | | |
|--|--|
| <input type="checkbox"/> involves a risk of a person falling more than 2 meters | <input type="checkbox"/> is carried out on or near pressurised gas mains or piping |
| <input type="checkbox"/> is carried out on a telecommunication tower | <input type="checkbox"/> is carried out on or near chemical, fuel or refrigerant lines |
| <input type="checkbox"/> involves demolition of an element of a structure that is load-bearing | <input type="checkbox"/> is carried out on or near energised electrical installations or services |
| <input type="checkbox"/> involves demolition of an element related to the physical integrity of a structure | <input type="checkbox"/> is carried out in an area that may have a contaminated or flammable atmosphere |
| <input type="checkbox"/> involves, or is likely to involve, disturbing asbestos | <input type="checkbox"/> involves tilt-up or precast concrete |
| <input type="checkbox"/> involves structural alteration or repair that requires temporary support to prevent collapse | <input type="checkbox"/> is carried out on, in or adjacent to a road, railway, shipping lane or other traffic corridor |
| <input type="checkbox"/> is carried out in or near a confined space | <input type="checkbox"/> is carried out in an area of a workplace where there is any movement of powered mobile plant |
| <input type="checkbox"/> is carried out in/near a shaft or trench deeper than 1.5m or tunnel involving use of explosives | <input type="checkbox"/> is carried out in areas with artificial extremes of temperature. |
| <input type="checkbox"/> is carried out in or near water or other liquid that involves a risk of drowning. | <input type="checkbox"/> involves diving work. |

ANY HIGH-RISK MACHINERY OR EQUIPMENT NEARBY

RISK MATRIX									
LIKELIHOOD	INSIGNIFICANT	MINOR	MODERATE	MAJOR	CATASTROPHIC	SCORE	ACTION	HEIRARCHY OF CONTROLS	
ALMOST CERTAIN	3 HIGH	3 HIGH	4 ACUTE	4 ACUTE	4 ACUTE			 <p>Elimination Remove the hazard.</p> <p>Substitution Replace the hazard.</p> <p>Isolation Isolate People from the hazard</p> <p>Engineering Isolate the hazard.</p> <p>Administrative Change the work.</p> <p>PPE</p>	
LIKELY	2 MODERATE	3 HIGH	3 HIGH	4 ACUTE	4 ACUTE	4A ACUTE	DO NOT PROCEED		
POSSIBLE	1 LOW	2 MODERATE	3 HIGH	4 ACUTE	4 ACUTE	3H HIGH	Review before work starts.		
UNLIKELY	1 LOW	1 LOW	2 MODERATE	3 HIGH	4 ACUTE	2M MODERATE	Ensure control measures in place.		
RARE	1 LOW	1 LOW	2 MODERATE	3 HIGH	3 HIGH	1L LOW	Monitor and keep records		

Notes on Hierarchy of Controls: Elimination methods are the most effective and preferred when controlling a hazard. Substitution is the second most effective method of controlling a hazard. Engineering by isolation is the third most effective, while Administrative Controls by changing the work is the fourth most effective method. PPE (Personal Protective Equipment) is the least effective method.

PERSONAL PROTECTIVE EQUIPMENT (PPE)											
Select the appropriate PPE above suitable for the equipment used or the job task being performed (if applicable).											
FOOT PROTECTION	HAND PROTECTION	HEAD PROTECTION	HEARING PROTECTION	EYE PROTECTION	RESPIRATORY PROTECTION	FACE PROTECTION	HIGH-VIS CLOTHING	PROTECTIVE CLOTHING	FALL PROTECTION	SUN PROTECTION	HAIR/JEWELLERY SECURED
											
<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
Other PPE Required:											
Permit or Licenses Requirements						Mandatory Qualifications and Training					

JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
Pre-start planning and documentation	<ul style="list-style-type: none"> Unclear scope of work Unidentified live electrical circuits Incomplete isolation documentation Conflicting renovation activities Inadequate emergency planning 	3H	<ul style="list-style-type: none"> Review plans, single-line diagrams and specifications before starting work and confirm scope of maintenance, repairs, renovations and upgrades with the principal contractor or client Identify all relevant circuits, switchboards and equipment on drawings and physically verify circuit labelling against installed equipment Complete a task-specific risk assessment and Safe Work Method Statement for electrical maintenance, fault finding, installation, repairs and renovations and have it reviewed by a competent person Confirm whether proposed work involves high-risk construction work under WHS Regulations (e.g. work on or near energised electrical installations, high rise electrical servicing, work in or near confined spaces) and apply additional controls and permits as required Consult with other trades on site to identify overlapping works that may affect electrical safety, including demolition, carpentry, plumbing or mechanical works Establish communication procedures, including who has authority to energise or de-energise circuits and who is the site contact for co-ordination Prepare an emergency response plan covering electric shock, fire and arc flash events, and display relevant emergency contact numbers and site address near the main switchboard Verify that all required test instruments, isolation and lockout devices, tags, insulated tools and PPE are on site, in test and within calibration dates to AS/NZS 3017 and AS/NZS 3760 where applicable DO NOT commence work until all required permits, access approvals and isolation documents are in place and signed 	2M
Site inspection and work area setup	<ul style="list-style-type: none"> Uneven walking surfaces Unstable access equipment Overhead service contact Unauthorised public access Poor lighting levels Trip hazards from leads and materials 	3H	<ul style="list-style-type: none"> Walk the work area and identify slip, trip and fall hazards such as loose debris, wet floors, trailing cables and open penetrations, then remove or barricade them Confirm location and height of overhead powerlines and service cables before positioning ladders, EWPs or scaffolds, and maintain clearances in accordance with local network operator requirements Set up physical barriers, cones and warning signs to separate the electrical work area from public access and other trades, especially in corridors, foyers and high rise common areas Arrange adequate task lighting using low voltage or battery-powered work lights in accordance with AS/NZS 3012, ensuring lights and leads are secured to prevent falls and trips Route extension leads overhead or along edges where practicable, secure with tape or cable covers, and use only heavy-duty leads tested and tagged to AS/NZS 3760 Select stable, industrial rated ladders to AS/NZS 1892 and ensure they are placed on firm, level ground and secured where possible DO NOT block emergency exits, fire equipment or access to switchboards with tools, ladders or materials 	2M

JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
Isolating low voltage installations	<ul style="list-style-type: none"> Inadvertent contact with live parts Backfeed from alternate supplies Incorrect circuit isolation Unexpected re-energisation Stored energy in capacitors 	4A	<ul style="list-style-type: none"> Identify all sources of supply including mains, generators, UPS, solar PV, battery systems and control transformers before any work on low voltage electrical repairs and installations Operate main switches, circuit breakers or isolators to de-energise the specific circuit or switchboard section required for the task in accordance with AS/NZS 4836 Apply personal locks and durable danger tags to each isolation point, noting name, contact number, date and reason for isolation Use a test-approved voltage tester verified on a known live source immediately before and after use to prove de-energisation at the point of work Discharge any capacitors or stored energy devices using approved discharge tools and follow manufacturer instructions before touching conductors or terminals Install lockable covers, shields or insulating barriers over adjacent live parts where they cannot be de-energised and must remain energised for operational reasons Record isolation points and affected circuits on an isolation form or permit to work and keep it with the person in control of the work DO NOT rely solely on circuit labelling or breaker position; always test for dead at the point of work DO NOT remove another person's lock or tag without following a documented lock removal procedure authorised by the person in control of the workplace 	2M
Fault finding and testing on circuits	<ul style="list-style-type: none"> Electric shock from live testing Arc flash during measurement Unexpected equipment start-up Short circuit from test leads Exposure to faulty insulation 	4A	<p>[REDACTED]</p> <p>[REDACTED]</p> <p>[REDACTED]</p> <p>[REDACTED]</p> <p>[REDACTED]</p> <p>[REDACTED]</p> <p>[REDACTED]</p> <p>[REDACTED]</p>	3H

JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
Switchboard access and repairs	<ul style="list-style-type: none"> • Arc flash from switchboard fault • Contact with exposed busbars • Improper neutral or earth connections • Overheating from loose terminations • Inhalation of arc products 	4A		2M
Rewiring and expansion of systems	<ul style="list-style-type: none"> • Incorrect cable selection • Damage to existing services • Cable overloading • Fire from poor terminations • Dust and debris inhalation 	3H		2M

[illegible]

JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
Renovations and re-routing for automation	<ul style="list-style-type: none"> • Interference with automatic systems • Unintended equipment operation • Control circuit misidentification • Exposure to low voltage control faults • Network and data cable damage 	3H	<p>[REDACTED]</p> <p>[REDACTED]</p> <p>[REDACTED]</p> <p>[REDACTED]</p> <p>[REDACTED]</p> <p>[REDACTED]</p> <p>[REDACTED]</p> <p>[REDACTED]</p> <p>[REDACTED]</p> <p>[REDACTED]</p>	2M
High rise electrical servicing access	<ul style="list-style-type: none"> • Working at heights on ladders • Falling objects from height • Limited egress in risers • Manual handling of heavy gear • Elevator and lobby public exposure 	3H	<p>[REDACTED]</p> <p>[REDACTED]</p> <p>[REDACTED]</p> <p>[REDACTED]</p> <p>[REDACTED]</p> <p>[REDACTED]</p> <p>[REDACTED]</p>	2M

JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
Installing and replacing electrical equipment	<ul style="list-style-type: none"> • Connecting faulty new equipment • Non-compliant appliance installation • Mechanical instability of fixtures • Excessive inrush or fault current • Sharp edges and cuts 	3H		1L
Working near existing live services	<ul style="list-style-type: none"> • Contact with concealed live cables • Penetration into services • Induced voltages in nearby conductors • Damage to fire and security systems • Exposure to asbestos-containing materials 	4A		2M

JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
			<div></div> <div></div> <div></div> <div></div> <div></div> <div></div>	
Verification testing and re-energisation	<ul style="list-style-type: none"> • Energising unsafe circuits • Failure of protective devices • Electric shock during testing • Unexpected load start-up • Incorrect RCD operation 	4A	<div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div>	2M

JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
Documentation, handover and housekeeping	<ul style="list-style-type: none"> • Incorrect as-built information • Uninformed occupants or users • Residual debris and offcuts • Unsecured leftover materials • Inadequate maintenance instructions 	2M	<div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> </div>	1L

EMERGENCY RESPONSE – CALL 000 FOR EMERGENCIES

Ensure to have an Emergency Management Plan in place as well as adequate numbers of trained first aid staff with easy access to fully stocked first aid kits, rescue equipment, material safety data sheets, adequate access to emergency communication equipment and fire-fighting equipment suitable for all classes of fire and ignition sources.

LEGISLATIVE REFERENCES

RELEVANT LEGISLATION AND CODES OF PRACTICE. DELETE THE LEGISLATIVE REFERENCES IF ANY STATE IS NOT APPLICABLE

Queensland & Australian Capital Territory

Work Health and Safety Act 2011

Work Health and Safety Regulations 2011

Legislation QLD: <https://www.worksafe.qld.gov.au/laws-and-compliance/work-health-and-safety-laws>

Codes of Practice QLD: <https://www.worksafe.qld.gov.au/laws-and-compliance/codes-of-practice>

Legislation ACT: <https://www.worksafe.act.gov.au/laws-and-compliance/acts-and-regulations>

Codes of Practice ACT: <https://www.worksafe.act.gov.au/laws-and-compliance/codes-of-practice>

Victoria

Occupational Health and Safety Act 2004

Occupational Health and Safety Regulations 2017

Legislation VIC: <https://www.worksafe.vic.gov.au/occupational-health-and-safety-act-and-regulations>

Codes of Practice VIC: <https://www.worksafe.vic.gov.au/compliance-codes-and-codes-practice>

New South Wales

Work Health and Safety Act 2011

Work Health and Safety Regulations 2025

Legislation NSW: <https://www.safework.nsw.gov.au/legal-obligations/legislation>

Codes of Practice NSW: <https://www.safework.nsw.gov.au/resource-library/list-codes-of-practice>

Western Australia

Work Health and Safety Act 2020

Work Health and Safety Regulations 2022

Legislation Western Australia: <https://www.commerce.wa.gov.au/worksafe/legislation>

Codes of Practice WA: <https://www.commerce.wa.gov.au/worksafe/codes-practice>

Northern Territory

Work Health and Safety (National Uniform Legislation) Act 2011

Work Health and Safety (National Uniform Legislation) Regulation 2011

Legislation NT: <https://worksafe.nt.gov.au/laws-and-compliance/workplace-safety-laws>

Codes of Practice NT: <https://worksafe.nt.gov.au/factsheets-and-resources/codes-of-practice>

Safe Work Australia Links

Law and Regulation (All States): <https://www.safeworkaustralia.gov.au/law-and-regulation>

Model Codes of Practice: <https://www.safeworkaustralia.gov.au/resources-publications/model-codes-of-practice>

Model Codes of Practice

- Managing noise and preventing hearing loss at work
- Confined spaces
- Labelling of workplace hazardous chemicals
- Managing risks of hazardous chemicals in the workplace
- Welding processes
- First aid in the workplace
- Managing the risk of falls at workplaces
- Hazardous manual tasks
- Managing the risk of falls in housing construction
- Managing electrical risks in the workplace
- Demolition work
- Excavation work
- Work health and safety consultation, cooperation and coordination
- Managing the work environment and facilities
- How to manage work health and safety risks
- Managing risks of plant in the workplace
- Construction work

South Australia

Work Health and Safety Act 2012 (SA)

Work Health and Safety Regulations 2012 (SA)

Legislation for SA: <https://www.safework.sa.gov.au/resources/legislation>

Codes of Practice for SA: <https://www.safework.sa.gov.au/workplaces/codes-of-practice#COPs>

Tasmania

Work Health and Safety Act 2012

Work Health and Safety (Transitional and Consequential Provisions) Act 2012

Work Health and Safety Regulations 2012

Work Health and Safety (Transitional) Regulations 2012

Legislation for TAS: <https://worksafe.tas.gov.au/topics/laws-and-compliance/acts-and-regulations>

Codes of Practice for TAS: <https://worksafe.tas.gov.au/topics/laws-and-compliance/codes-of-practice>

Details of permits, licenses or access required by regulatory bodies (add or delete as required):

- Permits from local council
- Authorisation to commence work
- Any required documents.

SIGNATORIES OF THE SAFE WORK METHOD STATEMENT

The signed and dated personnel listed below have cooperated in the consultation and development of this Safe Work Method Statement which has been approved by the Person/s Conducting a Business or Undertaking (PCBU). In signing this Safe Work Method Statement each individual acknowledges and confirms that they have read this SWMS in full, having raised any questions for items on this Safe Work Method Statement that require clarification, and confirms that they are competent, skilled and knowledgeable for the task assigned to them. Every person acknowledges that they have received the relevant training and qualifications where required, before carrying out any work contained in this Safe Work Method Statement. By signing this Safe Work Method Statement each individual agrees to work safely, to follow any safe work instructions which are provided, and agrees to use all Personal Protective Equipment where appropriate.

Worker Name	Signature	Date

SAFE WORK METHOD STATEMENT MONITORING AND REVIEW

The SWMS must be reviewed regularly to make sure it remains effective and must be reviewed (and revised if necessary) if relevant control measures are revised. The review must be carried out in consultation with workers (including contractors and sub-contractors) who may be affected by the operation of the SWMS and their health and safety representatives who represent that work group at the workplace.

When the SWMS has been revised the PCBU must ensure that all persons involved with the work are advised that a revision has been made and how they can access the revised SWMS, including all persons who will need to change a work procedure or system as a result of the review are advised of the changes in a way that will enable them to implement their duties consistently with the revised SWMS. All workers that will be involved in the work must be provided with the relevant information and instruction that will assist them to understand and implement the revised SWMS.

The SWMS must be monitored regularly for the effectiveness of ensuring hazard controls are effective in reducing the risk of incidents, keeping the workplace safe for all personnel. The person responsible for monitoring the effectiveness of the Safe Work Method Statement should employ a multi-faceted approach which includes but is not limited to:

1. Spot Checks.
2. Consultation with workers, contractors and sub-contractors.
3. Internal audits on a continual basis.

An approach of continuous improvement, promptly recording inconsistencies or deficiencies, followed up by immediate corrective action and consultation with all relevant personnel ensures that the PCBU is consistently developing ever-improving systems of safe work principles.

REVIEW NUMBER	1	2	3	4	5	6	7
NAME							
INITIALS							
DATE							

SAFE WORK METHOD STATEMENT REVIEW CHECKLIST

This Safe Work Method Statement Review Checklist is to be followed and used upon initial development of the SWMS to help ensure that all steps have been adequately taken before work commences. Think of this document as an internal audit review checklist before commencing work, and may form part of a Toolbox Talk (safety meeting) and may be used as an opportunity for education and training.

ITEMS WHICH MUST BE INCLUDED IN THE SWMS	COMPLETED	COMMENTS
The company details have been entered, including the project name and address.	<input checked="" type="checkbox"/>	
All relevant personnel consulted during the development of the SWMS.	<input checked="" type="checkbox"/>	
Name, signature, position and date signed of the person approving the SWMS.	<input type="checkbox"/>	
Specific personnel and qualifications, experience is noted in the SWMS.	<input checked="" type="checkbox"/>	
Provides a step-by-step process of tasks required to carry out the activity or task.	<input checked="" type="checkbox"/>	
Adequate risk assessment of any identified hazards has been completed.	<input checked="" type="checkbox"/>	
Foreseeable hazards are identified and documented for each step.	<input checked="" type="checkbox"/>	
Any hazards listed in any site risk assessments have been added to the SWMS.	<input checked="" type="checkbox"/>	
SWMS initial risk (IR) column as well as residual risk (RR) column completed.	<input checked="" type="checkbox"/>	
Check control measures added to the SWMS are the most effective selected.	<input checked="" type="checkbox"/>	
Responsible person is assigned and listed on the SWMS for the implementation of control measures.	<input checked="" type="checkbox"/>	
Permit or licenses requirements specified, such as Hot Work, Electrical Work, Work at Heights etc.	<input checked="" type="checkbox"/>	
SWMS identifies plant and equipment to be used.	<input checked="" type="checkbox"/>	
Details of inspection checks required for any equipment listed and noted on the SWMS.	<input checked="" type="checkbox"/>	
Describes any mandatory qualifications, experience, training or skills required to perform the work.	<input checked="" type="checkbox"/>	
Applicable personal protective equipment is selected on the SWMS.	<input checked="" type="checkbox"/>	
Reflects and documents any legislative references and/or Australian Standards.	<input checked="" type="checkbox"/>	
Identifies any hazardous substances used with specific control measures in line with any SDS.	<input checked="" type="checkbox"/>	
REVIEWED BY		DATE REVIEWED
SIGNATURE		DATE COMPLETED