



| Industrial Radiography \   | Work   SAFE WORK METH  | OD STATEMENT (SWMS)                      |                                     |
|--|--|--|-------------------------------------|
| TASK O   | R ACTIVITY: Industrial Radiogra                              | ohy Work                                 |                                     |
| Business Name:   |  | ABN:                                     | SWMS#                               |
| Business Address:  |  |  |                                     |
| Contact Person:  | Phone:   | E 111:                                   |                                     |
|  |  |  |                                     |
| THIS SAFE WORK METHOD  | STATEMENT IS APPROVED BY                                     | THE PCL OF THE ROJECT                    |                                     |
| Under the Work Health and Safety Regulation (WHS Regulation), a person conduct the proposed work starts.   | cting a business or under the (PC 1) is                      | required to en that a safe work method s | statement (SWMS) is prepared before |
| Full Name:   |  |  |                                     |
| Signature:   | NY   | Title:                                   | Date:                               |
| Details of the person(s) responsible for ensuring implementation, monitoring   | opliance the VMS a well as review                            | s and modifications of the SWMS.         |                                     |
| Full Name:   |  | Title:                                   | Phone:                              |
| ALL PERSONNEL PARTICIPATING IN ANY ACTIVITY ON THIS MIS MIS MIS MIS MIS MIS MIS MIS MIS M  | NA, ¿ OF ALL RELEVANT PERSONNI<br>EVELOPMENT AND APPROVAL OF | EL WHO HAVE BEEN CONSULTED AND CO        | OMMUNICATED TO IN THE               |
| Safety meetings or toolbox talks will be sched ed in accomply with gislative requirements to first identify any site hazards, hazards and then to further take steps to either eliminate or continuate hazard.   |  |  |                                     |
| If an incident or a near miss occurs, all work must sto, an alately. Depending on the severity of the incident, a meeting will be called with all workers to amend the SWMS if required. The meeting may also be an educational opportunity.   |  |  |                                     |
| Any changes made to the SWMS after an incident or a near miss must be approved by the Person Conducting Business or Undertaking and communicated to all relevant personnel.  |  |  |                                     |
| The SWMS must be kept and be available for inspection at least until the work is completed. Where a SWMS is revised, all versions should be kept. If a notifiable incident occurs in relation to which the SWMS relates, then the SWMS must be kept for at least two years from the occurrence of the notifiable incident. |  |  |                                     |

Version 2.5 Authorised by Review # Date of Issue: Review Date: 1





| CLIENT OR PRINCIPAL  | CONTRACTOR DETAILS  |
|--|---|
| Client:  | SCOPE OF WORKS  |
| Project Name:  |   |
| Project Address:   |   |
| Project Manager:   |   |
| Contact Phone:   |   |
| Date SWMS supplied to Project Manager:   |   |
| ANY HIGH BIOK CONSTRUCTOR  | NAME OF THE POLIT   |
| ANY HIGH-RISK CONSTRUCTOR  | N WC & BEIN C ARIED OUT   |
| ☐ involves a risk of a person falling more than 2 meters                                     | is carried out on or near pressurised gas mains or piping                                       |
| ☐ is carried out on a telecommunication tower  | carried out on or near chemical, fuel or refrigerant lines                                      |
| ☐ involves demolition of an element of a structure that is load-bearing                      | $\square$ is carried out on or near energised electrical installations or services              |
| ☐ involves demolition of an element related to the physical integral of a functure           | ☐ is carried out in an area that may have a contaminated or flammable atmosphere                |
| ☐ involves, or is likely to involve, disturbing asb  | ☐ involves tilt-up or precast concrete  |
| ☐ involves structural alteration or repair that —quires term — v sup —rt to prevent collapse | ☐ is carried out on, in or adjacent to a road, railway, shipping lane or other traffic corridor |
| ☐ is carried out in or near a confined space   | ☐ is carried out in an area of a workplace where there is any movement of powered mobile plant  |
| ☐ is carried out in/near a shaft or trench deeper that. tunnel involving use of explosives   | ☐ is carried out in areas with artificial extremes of temperature.                              |
| $\square$ is carried out in or near water or other liquid that involves a risk of drowning.  | ☐ involves diving work.   |
| ANY HIGH-RISK MACHINER   | Y OR EQUIPMENT NEARBY   |
|  |   |
|  |   |
|  |   |

Version 2.5 Authorised by Review # Date of Issue: Review Date: 2



| RISK MATRIX       |  |               |               |            |              |                |                                   |                                 |  |
|-------------------|--|---------------|---------------|------------|--------------|----------------|-----------------------------------|---------------------------------|--|
| LIKELIHOOD        | INSIGNIFICANT  | MINOR         | MODERATE      | MAJOR      | CATASTROPHIC | SCORE          | ACTION                            | HEIRARCHY OF CONTROLS           |  |
| ALMOST<br>CERTAIN | 3<br>HIGH  | 3<br>HIGH     | 4<br>ACUTE    | 4<br>ACUTE | 4<br>ACUTE   | SCORE ACTION   | Elimination Remove the hazard.    |                                 |  |
| LIKELY            | 2<br>MODERATE  | 3<br>HIGH     | 3<br>HIGH     | 4<br>ACUTE | 4<br>ACUTE   | 4A<br>ACUTE    | DO NOT<br>PROCE                   | Substitution                    |  |
| POSSIBLE          | 1<br>LOW   | 2<br>MODERATE | 3<br>HIGH     | 4<br>ACUTE | 4<br>ACUTE   | 3H<br>HIGH     | Review before work starts.        | Replace the hazard.             |  |
| UNLIKELY          | 1<br>LOW   | 1<br>LOW      | 2<br>MODERATE | 3<br>HIGH  | 4<br>ACUTE   | 2M<br>MODERATE | Ensure control measures in place. | Isolate People from the hazard  |  |
| RARE              | 1<br>LOW   | 1<br>LOW      | 2<br>MODERATE | 3<br>HIGH  | 3<br>HIGH    | 1L<br>LOW      | nitor and                         | Engineering Isolate the hazard. |  |
| is the second m   | the second most effective method of controlling a hazard. Engineering by isolation is the five ost energies on the second most effective method of controlling a hazard. PPE (Personal Protective Equipment) whe least effective |               |               |            |              |                |                                   |                                 |  |

|                    |                    |                    |                  | PERS        |                       | TIVE EQUIPM                           |                      |                        |                    |                   |                           |
|--------------------|--------------------|--------------------|------------------|-------------|-----------------------|---------------------------------------|----------------------|------------------------|--------------------|-------------------|---------------------------|
|                    |                    | Select the app     | propriate PPL    | abo√ ≃uitab | ic or the equi        | pment used or                         | the job task         | being perforr          | ned (if applica    | ıble).            |                           |
| FOOT<br>PROTECTION | HAND<br>PROTECTION | HEAD<br>PROTECTION | HEARING<br>ETION | P ECTION    | R PIRATORY PROTECTION | FACE<br>PROTECTION                    | HIGH-VIS<br>CLOTHING | PROTECTIVE<br>CLOTHING | FALL<br>PROTECTION | SUN<br>PROTECTION | HAIR/JEWELLERY<br>SECURED |
|                    |                    |                    |                  |             |                       |                                       |                      |                        |                    |                   |                           |
|                    |                    |                    |                  |             |                       |                                       |                      |                        |                    |                   |                           |
| Other PPE R        | Required:          |                    |                  |             |                       |                                       |                      |                        |                    |                   |                           |
|                    | Pe                 | ermit or Licen     | ses Requirem     | ents        |                       | Mandatory Qualifications and Training |                      |                        |                    |                   |                           |
|                    |                    |                    |                  |             |                       |                                       |                      |                        |                    |                   |                           |
|                    |                    |                    |                  |             |                       |                                       |                      |                        |                    |                   |                           |
|                    |                    |                    |                  |             |                       |                                       |                      |                        |                    |                   |                           |



| JOB STEP            | POTENTIAL HAZARDS                           | IR              | CONTROL MEASURES  | RR               |
|---------------------|---|-----------------|---|------------------|
| SPECIFIC WORK STEPS | HAZARDS THAT MAY ARISE                      | INITIAL<br>RISK | SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS  | RESIDUAL<br>RISK |
| 1. Preparation      | Radiation Exposure, Slips and Falls         | 2M              | <ul> <li>Conduct a risk assessment prior to startip to e work to identify potential radiation exposure and physical hazards.</li> <li>Provide comprehensive training for personne promation safety and safe handling procedures.</li> <li>Use appropriate personal protective equipment (PE) such a read aprons, gloves, and suitable footwear to mitigate radiation prosure and prevent lips of ralls.</li> <li>Establish and clear and design ted radiation zone, with warning signs to restrict access to authorised personnel only.</li> <li>Implement a exclusion to be around a mography area within which non-essential personnel are prohibited durin expositions.</li> <li>Use in the control where possible to maintain a safe distance from radiation sources during operation.</li> <li>Regultify to brate of maintain radiation detection equipment to ensure accurate monitoring of radiation leve.</li> <li>Inspect of maintain scaffolding and ladders regularly to ensure stability and safety compliance.</li> <li>Tovide adequate lighting in all areas where radiography work is conducted to reduce the risk of tripping and falling.</li> <li>Install handrails and guardrails in areas prone to slips and falls for additional worker support and safety.</li> <li>Rotate tasks among workers to limit exposure time to radiation and reduce fatigue, which can lead to accidents.</li> <li>Schedule regular health check-ups and monitoring for personnel potentially exposed to ionising radiation.</li> <li>Keep detailed records of individual radiation exposure using dosimeters to track any instances of overexposure and enhance safety protocols.</li> </ul> | 1L               |
| 2. Equipment Check  | Equipment Malfunction, Electrical<br>Shocks | ЗН              | <ul> <li>Conduct thorough pre-work inspections of all radiography equipment to identify any signs of wear or damage.</li> <li>Ensure that all electrical components are regularly maintained and serviced by a qualified technician.</li> <li>Use equipment only as per the manufacturer's instructions and recommendations.</li> <li>Implement a regular training program for workers to recognise and respond to equipment malfunctions and electrical hazards.</li> <li>Ensure that all electrical connections and cables are properly insulated and protected from environmental damage.</li> </ul>   | 1L               |



| JOB STEP               | POTENTIAL HAZARDS  | IR              | CONTROL MEASURES   | RR               |
|------------------------|--|-----------------|--|------------------|
| SPECIFIC WORK STEPS    | HAZARDS THAT MAY ARISE                                   | INITIAL<br>RISK | SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS   | RESIDUAL<br>RISK |
|                        |  |                 | - Develop and enforce a lock-out/tag-out (LOTO) procedure to guarantee equipment is safely de-<br>energised during maintenance or inspection.                            |                  |
|                        |  |                 | - Provide non-conductive personal protective equipment, such as insulated gloves and boots, for workers handling electrical equipment.                                   |                  |
|                        |  |                 | - Include ground fault circuit interrupters ( s) in power ircuits to protect against electrical shock.   |                  |
|                        |  |                 | - Maintain an up-to-date inventory of frequency of pesson of equipment checks with documented outcomes and preventative actions taken.                                   |                  |
|                        |  |                 | - Have emergency response as readily available and embed all workers know the immediate steps to take in case of an equipment manner.                                    |                  |
|                        |  |                 | - Store equipment in a concluded a pronounce to be stored as a concluded a pronounce to conditions a could cause a munction.   |                  |
|                        |  |                 | - Verificall equations seems features, seems as emergency shut-off switches and warning lights, are operated before seeing work.   |                  |
|                        |  |                 | - Appoint a spetch personnel familiar with both the equipment and potential hazards to oversee safety protocol an ensure entrols are adhered to on site.                 |                  |
|                        |  |                 | - aduct a pre-to asport vehicle inspection to ensure the vehicle is in good working condition, including brake.  |                  |
|                        |  |                 | lse certimed and approved containers specifically designed for transporting radioactive sources, entring they are securely locked and sealed.                            |                  |
|                        |  |                 | Ensure all personnel involved in transport have completed relevant training in radiation safety and emergency procedures.  |                  |
|                        |  |                 | - Display appropriate placards and labels on the transport vehicle indicating the presence of radioactive materials in accordance with regulatory requirements.          |                  |
|                        |  |                 | - Equip the transport vehicle with necessary safety equipment, such as fire extinguishers, spill kits, and personal protective equipment (PPE) for emergencies.          |                  |
| 3. Transport of Source | Accident during Transport, ntrolled Release of Radiation | 4A              | - Plan and select routes that minimise travel time and avoid densely populated areas or areas with known roadworks whenever possible.                                    | 2M               |
|                        |  |                 | - Establish a communication protocol for regular check-ins during transport, including an established response plan for any accidents or delays.                         |                  |
|                        |  |                 | - Ensure compliance with Australian Dangerous Goods (ADG) Code and other relevant regulations governing the transport of radioactive materials.                          |                  |
|                        |  |                 | - Implement double-check procedures for source identification numbers and documentation before and after transport.  |                  |
|                        |  |                 | - Limit transport times to daylight hours to reduce risks associated with night-time driving whenever feasible.  |                  |
|                        |  |                 | - Maintain a detailed log of transport activities, including timings, personnel involved, route taken, and any incidents or observations, for accountability and review. |                  |



| JOB STEP                                | POTENTIAL HAZARDS                       | IR              | CONTROL MEASURES   | RR               |
|---|---|-----------------|--|------------------|
| SPECIFIC WORK STEPS                     | HAZARDS THAT MAY ARISE                  | INITIAL<br>RISK | SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS | RESIDUAL<br>RISK |
| 4. Source Loading                       | Radiation Exposure, Equipment Fault     | ЗН              |  | 1L               |
| 5. Positioning of<br>Radiography Camera | Radiation Exposure, Trip & Fall Hazards | 2M              |  | 1L               |



| JOB STEP            | POTENTIAL HAZARDS                                      | IR              | CONTROL MEASURES   | RR               |
|---------------------|--|-----------------|--|------------------|
| SPECIFIC WORK STEPS | HAZARDS THAT MAY ARISE                                 | INITIAL<br>RISK | SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS | RESIDUAL<br>RISK |
| 6. Area Clearance   | Non-compliance to lear round, Inadequate Warning eight | BH              |  | I 1L             |



| JOB STEP                          | POTENTIAL HAZARDS                      | IR              | CONTROL MEASURES   | RR               |
|-----------------------------------|--|-----------------|--|------------------|
| SPECIFIC WORK STEPS               | HAZARDS THAT MAY ARISE                 | INITIAL<br>RISK | SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS | RESIDUAL<br>RISK |
| 7. Testing Procedure              | Radiation Exposure, Incorrect Readings | 2M              |  | 1L               |
| 8. Monitor Radiography<br>Process | Fail to Detect Leaks, Software Bugs    | 2M              |  | <b> </b> 1L      |



| JOB STEP                          | POTENTIAL HAZARDS          | IR              | CONTROL MEASURES   | RR               |
|-----------------------------------|----------------------------|-----------------|--|------------------|
| SPECIFIC WORK STEPS               | HAZARDS THAT MAY ARISE     | INITIAL<br>RISK | SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS | RESIDUAL<br>RISK |
|                                   |                            |                 |  |                  |
|                                   |                            |                 |  | I                |
| 9. Removing Exposure<br>Container | Accidental Droppin Survivo | ВН              |  | 1L               |
|                                   |                            |                 |  | ,                |



| JOB STEP                         | POTENTIAL HAZARDS                               | IR              | CONTROL MEASURES   | RR               |
|----------------------------------|---|-----------------|--|------------------|
| SPECIFIC WORK STEPS              | HAZARDS THAT MAY ARISE                          | INITIAL<br>RISK | SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS | RESIDUAL<br>RISK |
| 10. Transport of Exposure Device | Accidents during Transport, Unauthorized Access | ЗН              |  | 2M               |
| 11. Source Unloading             | Radiation Exposure, Equipment Malfunctions      | 3H              |  | 1L               |



| JOB STEP                     | POTENTIAL HAZARDS                           | IR              | CONTROL MEASURES   | RR               |
|------------------------------|---|-----------------|--|------------------|
| SPECIFIC WORK STEPS          | HAZARDS THAT MAY ARISE                      | INITIAL<br>RISK | SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS | RESIDUAL<br>RISK |
|                              |   |                 |  |                  |
|                              |   |                 |  |                  |
|                              |   |                 |  |                  |
|                              |   |                 |  |                  |
|                              |   |                 |  |                  |
|                              |   |                 |  | •                |
|                              |   |                 |  |                  |
|                              |   |                 |  |                  |
|                              |   |                 |  |                  |
| 12. Post-operation<br>Checks | Misinterpret Test Results, Equipment Faults | 2M              |  | 1L               |
|                              |   |                 |  |                  |
|                              |   |                 |  |                  |
|                              |   |                 |  |                  |
|                              |   |                 |  |                  |



| JOB STEP            | POTENTIAL HAZARDS                                       | IR              | CONTROL MEASURES   | RR               |
|---------------------|---|-----------------|--|------------------|
| SPECIFIC WORK STEPS | HAZARDS THAT MAY ARISE                                  | INITIAL<br>RISK | SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS | RESIDUAL<br>RISK |
| 13. Waste Disposal  | Improper Waste Handling,<br>Environmental Contamination |                 |  | 1L               |
| 14. Decontamination | Inadequate Decontamination, Cross-contamination         | ЗН              |  | 2M               |



| JOB STEP                       | POTENTIAL HAZARDS               | IR              | CONTROL MEASURES   | RR               |
|--------------------------------|---------------------------------|-----------------|--|------------------|
| SPECIFIC WORK STEPS            | HAZARDS THAT MAY ARISE          | INITIAL<br>RISK | SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS | RESIDUAL<br>RISK |
|                                |                                 |                 |  |                  |
| 15. Maintenance and<br>Storage | Faulty Equipments, Unau. Access | ЗН              |  | 2M               |



| JOB STEP                    | POTENTIAL HAZARDS                                   | IR              | CONTROL MEASURES   | RR               |
|-----------------------------|---|-----------------|--|------------------|
| SPECIFIC WORK STEPS         | HAZARDS THAT MAY ARISE                              | INITIAL<br>RISK | SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS | RESIDUAL<br>RISK |
|                             |   |                 |  |                  |
|                             |   |                 |  |                  |
| 16. Emergency<br>Response   | Insufficient Training, Lack of Emergenc<br>Supplies | 3H              |  | 2M               |
|                             | 5   |                 |  | •                |
| 17. Reviewing<br>Procedures | Non-adherence to Protocol, Human error              | 2M              |  | 1L               |



| JOB STEP                        | POTENTIAL HAZARDS  | IR              | CONTROL MEASURES   | RR               |
|---------------------------------|--|-----------------|--|------------------|
| SPECIFIC WORK STEPS             | HAZARDS THAT MAY ARISE                                   | INITIAL<br>RISK | SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS | RESIDUAL<br>RISK |
|                                 |  |                 |  |                  |
| 18. Reporting and Documentation | Data Mismanagement, Non-compliance to Reporting Standard | 2M              |  | 1L               |
|                                 |  |                 |  |                  |



| JOB STEP            | POTENTIAL HAZARDS                               | IR              | CONTROL MEASURES   | RR               |
|---------------------|---|-----------------|--|------------------|
| SPECIFIC WORK STEPS | HAZARDS THAT MAY ARISE                          | INITIAL<br>RISK | SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS | RESIDUAL<br>RISK |
|                     |   |                 |  |                  |
| 19. Worker Training | Inadequate Training Lack of Safety<br>Awareness | ЗН              |  | 2M               |



| JOB STEP                   | POTENTIAL HAZARDS                                | IR              | CONTROL MEASURES   | RR               |
|----------------------------|--|-----------------|--|------------------|
| SPECIFIC WORK STEPS        | HAZARDS THAT MAY ARISE                           | INITIAL<br>RISK | SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS | RESIDUAL<br>RISK |
|                            |  |                 |  |                  |
| 20. Periodic<br>Assessment | Overlooked Hazards, Inconsistent Risk Assessment | 2M              |  | 1L               |
|                            |  |                 |  |                  |



#### **EMERGENCY RESPONSE - CALL 000 FOR EMERGENCIES**

Ensure to have an Emergency Management Plan in place as well as adequate numbers of trained first aid staff with easy access to fully stocked first aid kits, rescue equipment, material safety data sheets, adequate access to emergency communication equipment and fire-fighting equipment suitable for all classes of fire and ignition sources.

#### LEGISLATIVE REFERENCES

RELEVANT LEGISLATION AND CODES OF PRACTICE. DELETE THE LEGISLATIVE REFERENCES. ANY STATE OF AT ARE NOT APPLICABLE.

#### **Queensland & Australian Capital Territory**

Work Health and Safety Act 2011

Work Health and Safety Regulations 2011

 $\textbf{Legislation QLD:} \ \underline{\textbf{https://www.worksafe.qld.gov.au/laws-and-compliance/work-health-and-safety-laws}$ 

Codes of Practice QLD: https://www.worksafe.qld.gov.au/laws-and-compliance/codes-of-practice Legislation ACT: https://www.worksafe.act.gov.au/laws-and-compliance/acts-and-regulations

Codes of Practice ACT: https://www.worksafe.act.gov.au/laws-and-compliance/codes-of-practice

#### **New South Wales**

Work Health and Safety Act 2011

Work Health and Safety Regulations 2017

Legislation NSW: https://www.safework.nsw.gov.au/legal-obligations/legislative

Codes of Practice NSW: https://www.safework.nsw.gov.au/resource-library/lis codes-of ractions of Practice NSW: https://www.safework.nsw.gov.au/resource-library/lis codes-of-ractions-of-racti

#### **Northern Territory**

Work Health and Safety (National Uniform Legislation) Act 2011

Work Health and Safety (National Uniform Legislation) Regulation 201

Legislation NT: https://worksafe.nt.gov.au/laws-and-compliance/worksafe.nt.gov.au/laws-and-compl

Codes of Practice NT: https://worksafe.nt.gov.au/f

#### South Australia

Work Health and Safety Act 2012 (SA)

Work Health and Safety Regulations 2012 (SA)

Legislation for SA: https://www.safework.sa.gov.au/resources/le

Codes of Practice for SA: https://www.safework.sa.gov.au/work\_aces/codes-of-practice#COPs

#### Tasmania

Work Health and Safety Act 2012

Work Health and Safety (Transitional and Consequential Provisions) Act 2012

Work Health and Safety Regulations 2012

Work Health and Safety (Transitional) Regulations 2012

Legislation for TAS: https://worksafe.tas.gov.au/topics/laws-and-compliance/acts-and-regulations

Codes of Practice for TAS: https://worksafe.tas.gov.au/topics/laws-and-compliance/codes-of-practice

Details of permits, licenses or access required by regulatory bodies (add or delete as required):

- Permits from local council
- Authorisation to commence work
- Any required documents.

#### Victoria

Occupational Health at Safety Act 34

Occupational Health and Infety gulations 2017

Legis on VIC: https://www.wksafe.vic.gov.au/occupational-health-and-safety-act-and-

gulat

tes of actice VIC attps://www.worksafe.vic.gov.au/compliance-codes-and-codes-practice

#### Western Australia

Work Health and Safety Act 2020

Work Health and Safety Regulations 2022

Legislation Western Australia: https://www.commerce.wa.gov.au/worksafe/legislation

Codes of Practice WA: https://www.commerce.wa.gov.au/worksafe/codes-practice

#### Safe Work Australia Links

Law and Regulation (All States): https://www.safeworkaustralia.gov.au/law-and-regulation Model Codes of Practice: https://www.safeworkaustralia.gov.au/resources-publications/model-codes-of-practice

#### **Model Codes of Practice**

- Managing noise and preventing hearing loss at work
- Confined spaces
- Labelling of workplace hazardous chemicals
- Managing risks of hazardous chemicals in the workplace
- Welding processes
- First aid in the workplace
- Managing the risk of falls at workplaces
- Hazardous manual tasks
- Managing the risk of falls in housing construction
- Managing electrical risks in the workplace
- Demolition work
- Excavation work
- Work health and safety consultation, cooperation and coordination
- Managing the work environment and facilities
- How to manage work health and safety risks
- Managing risks of plant in the workplace
- Construction work





#### SIGNATORIES OF THE SAFE WORK METHOD STATEMENT

The signed and dated personnel listed below have cooperated in the consultation and development of this Safe Work Method Statement which has been approved by the Person/s Conducting a Business or Undertaking (PCBU). In signing this Safe Work Method Statement each individual acknowledges and confirms that they have read this SWMS in full, having raised any questions for items on this Safe Work Method Statement that require clarification, and confirms that they are competent, skilled and knowledgeable for the task assigned to them. Every person acknowledges that they have received the relevant training and qualifications where required, before carrying out any work contained in this Safe Work Method Statement. By signing this Safe Work Method Statement each individual agrees to work safely, to follow any safe work instructions which are provided, and agrees to use all Personal Protective Equipment where appropriate.

| Worker Name | Signature | Date |
|-------------|-----------|------|
|             |           |      |
|             |           |      |
|             |           |      |
|             |           |      |
|             |           |      |

#### SAFE WORK IN THE STATEMENT MONITORING AND REVIEW

The SWMS must be reviewed regularly to make sure it remains a fective of must be reviewed (and revised if necessary) if relevant control measures are revised. The view process should be carried out in consultation with workers (including contractors of the SWMS and their health and safety representatives who represented that work group at the workplace.

When the SWMS has been revised the PCBU mast ensure that advised that a revision has been made and how they can access the revised SWMS, including all persons who will need to change a work procedure or system as a rest of the review are advised of the changes in a way that will enable them to implement their duties and the involved in the work must be provided with the relevant information and instruction that will assist them to understand and implement the revised SWMS.

The SWMS must be monitored regularly for the effectiveness of ensuring hazard controls are effective in reducing the risk of incidents, keeping the workplace safe for all personnel. The person responsible for monitoring the effectiveness of the Safe Work Method Statement should employ a multi-faceted approach which includes but is not limited to:

- Spot Checks.
- 2. Consultation with workers, contractors and sub-contractors.
- 3. Internal audits on a continual basis.

An approach of continuous improvement, promptly recording inconsistencies or deficiencies, followed up by immediate corrective action and consultation with all relevant personnel ensures that the PCBU is consistently developing ever-improving systems of safe work principles.

| REVIEW NUMBER | 1 | 2 | 3 | 4 | 5 | 6 | 7 |
|---------------|---|---|---|---|---|---|---|
| NAME          |   |   |   |   |   |   |   |
| INITIALS      |   |   |   |   |   |   |   |
| DATE          |   |   |   |   |   |   |   |

Version 2.5 Authorised by Review # Date of Issue: Review Date: 19





### SAFE WORK METHOD STATEMENT REVIEW CHECKLIST

This Safe Work Method Statement Review Checklist is to be followed and used upon initial development of the SWMS to help ensure that all steps have been adequately taken before work commences. Think of this document as an internal audit review checklist before commencing work, and may form part of a Toolbox Talk (safety meeting) and may be used as an opportunity for education and training.

| ITEMS WHICH MUST BE INCLUDED IN THE SWMS   | COMPLETED  | COMMENTS |
|--|------------|----------|
|  |            |          |
| The company details have been entered, including the project name and address.   |            |          |
| All relevant personnel consulted during the development of the SWMS.   |            |          |
| Name, signature, position and date signed of the person approving the SWMS.  |            |          |
| Specific personnel and qualifications, experience is noted in the SWMS.  | 7          |          |
| Provides a step-by-step process of tasks required to carry out the activity or task.   |            |          |
| Adequate risk assessment of any identified hazards has been completed.   |            |          |
| Foreseeable hazards are identified and documented for each step.   |            |          |
| Any hazards listed in any site risk assessments have been added to the SWMS  |            |          |
| SWMS initial risk (IR) column as well as residual risk (RR) column mpleted.  |            |          |
| Check control measures added to the SWMS are the most effective selective.   |            |          |
| Responsible person is assigned and listed on the person is as a person is a per |            |          |
| Permit or licenses requirements specified, sur as Hot Work, Electric Work, Work at Heights etc.  |            |          |
| SWMS identifies plant and equipment to be us   |            |          |
| Details of inspection checks required for any equipment listed a noted on the SWMS.  |            |          |
| Describes any mandatory qualifications, experience, and or skills required to perform the work.  |            |          |
| Applicable personal protective equipment is selected on the SWMS.  |            |          |
| Reflects and documents any legislative references and/or Australian Standards.   |            |          |
| Identifies any hazardous substances used with specific control measures in line with any SDS.  |            |          |
|  |            |          |
| REVIEWED BY  | DATE REVIE | WED      |
| SIGNATURE  | DATE COMPL | ETED     |