



Installing Lights	SAFE WORK METHOD ST	ATEMENT (SWMS)	
TA	ASK OR ACTIVITY: Installing Lig	hts	
Business Name:		ABN:	SWMS#
Business Address:			
Contact Person:	Phone:	E fil:	
THIS SAFE WORK METHOD	STATEMENT IS APPROX D BY	THE PC. OF THE ROJECT	
Under the Work Health and Safety Regulation (WHS Regulation), a person conduct the proposed work starts.	cting a business or und	required to en that a safe work method	statement (SWMS) is prepared before
Full Name:			
Signature:	NY	Title:	Date:
Details of the person(s) responsible for ensuring implementation, monitoring a	poliance the VMS a well as review	vs and modifications of the SWMS.	
Full Name:		Title:	Phone:
ALL PERSONNEL PARTICIPATING IN ANY ACTIVITY ON THIS MANY HAVE THE FOLLOWING COMMUNICATED	NA. 2 OF ALL RELEVANT PERSONN EVELOPMENT AND APPROVAL OF	EL WHO HAVE BEEN CONSULTED AND C THIS SWMS	OMMUNICATED TO IN THE
Safety meetings or toolbox talks will be sched and in account with a gislative requirements to first identify any site hazards, and then to further take steps to either eliminate or continuous each hazard.			
If an incident or a near miss occurs, all work must sto, an atately. Depending on the severity of the incident, a meeting will be called with all workers to amend the SWMS if required. The meeting may also be an educational opportunity.			
Any changes made to the SWMS after an incident or a near miss must be approved by the Person Conducting Business or Undertaking and communicated to all relevant personnel.			
The SWMS must be kept and be available for inspection at least until the work is completed. Where a SWMS is revised, all versions should be kept. If a notifiable incident occurs in relation to which the SWMS relates, then the SWMS must be kept for at least two years from the occurrence of the notifiable incident.			

Version 2.5 Authorised by Review # Date of Issue: Review Date: 1





CLIENT OR PRINCIPAL	CONTRACTOR DETAILS
Client:	SCOPE OF WORKS
Project Name:	
Project Address:	
Project Manager:	
Contact Phone:	
Date SWMS supplied to Project Manager:	
ANY HIGH BIOK CONSTRUCTOR	NAME OF THE POLIT
ANY HIGH-RISK CONSTRUCTOR	N WC & BEIN C ARIED OUT
☐ involves a risk of a person falling more than 2 meters	is carried out on or near pressurised gas mains or piping
☐ is carried out on a telecommunication tower	carried out on or near chemical, fuel or refrigerant lines
☐ involves demolition of an element of a structure that is load-bearing	\square is carried out on or near energised electrical installations or services
☐ involves demolition of an element related to the physical integral of a functure	☐ is carried out in an area that may have a contaminated or flammable atmosphere
☐ involves, or is likely to involve, disturbing asb	☐ involves tilt-up or precast concrete
☐ involves structural alteration or repair that —quires term — v sup —rt to prevent collapse	☐ is carried out on, in or adjacent to a road, railway, shipping lane or other traffic corridor
☐ is carried out in or near a confined space	☐ is carried out in an area of a workplace where there is any movement of powered mobile plant
☐ is carried out in/near a shaft or trench deeper that. tunnel involving use of explosives	☐ is carried out in areas with artificial extremes of temperature.
\square is carried out in or near water or other liquid that involves a risk of drowning.	☐ involves diving work.
ANY HIGH-RISK MACHINER	Y OR EQUIPMENT NEARBY

Version 2.5 Authorised by Review # Date of Issue: Review Date: 2



RISK MATRIX									
LIKELIHOOD	INSIGNIFICANT	MINOR	MODERATE	MAJOR	CATASTROPHIC	SCORE	ACTION	HEIRARCHY OF CONTROLS	
ALMOST CERTAIN	3 HIGH	3 HIGH	4 ACUTE	4 ACUTE	4 ACUTE	SCORE	ACTION	Elimination Remove the hazard.	
LIKELY	2 MODERATE	3 HIGH	3 HIGH	4 ACUTE	4 ACUTE	4A ACUTE	DO NOT PROCE	Substitution	
POSSIBLE	1 LOW	2 MODERATE	3 HIGH	4 ACUTE	4 ACUTE	3H HIGH	Review before work starts.	Replace the hazard.	
UNLIKELY	1 LOW	1 LOW	2 MODERATE	3 HIGH	4 ACUTE	2M MODERATE	Ensure control measures in place.	Isolate People from the hazard	
RARE	1 LOW	1 LOW	2 MODERATE	3 HIGH	3 HIGH	1L LOW	nitor and	Engineering Isolate the hazard.	
is the second m	Administrative Otes on Hierarchy of Controls: Elimination methods are the most effective and preferrence on the second most effective method of controlling a hazard. Engineering by isolation is the life post entitive, while Administrative ontrols by changing the work is the fourth most effective method. PPE (Personal Protective Equament), the least effective								

				PERS		TIVE EQUIPM					
		Select the app	propriate PPL	abo√ ≃uitab	ic or the equi	pment used or	the job task	being perforr	ned (if applica	ıble).	
FOOT PROTECTION	HAND PROTECTION	HEAD PROTECTION	HEARING ETION	P ECTION	R PIRATORY PROTECTION	FACE PROTECTION	HIGH-VIS CLOTHING	PROTECTIVE CLOTHING	FALL PROTECTION	SUN PROTECTION	HAIR/JEWELLERY SECURED
Other PPE R	Required:										
	Pe	ermit or Licen	ses Requirem	ents			Ma	andatory Qual	ifications and	Training	



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
1. Preparation	Potential for slips, trips, and falls on uneven ground, Exposure to sharp objects	2M	 Conduct a pre-work site assessment to ideally and mark potential hazards such as uneven ground. Ensure all workers wear appropriate person protect or equipment, including steel-toe boots and gloves. Use signage to warn of tripp stards in the work site. Clear the work area of unneces any materials and site before starting. Utilise barriers of ones solefing only have as comprove visibility and hazard detection. Implement a haseker ong schedule to regularly check and maintain the site's cleanliness. Train is one as one ellifting techniques and the importance of maintaining awareness of their surrounding. Supply irst-tokits and ensure workers are briefed on emergency procedures in case of an injury. nait the number of people in high-risk areas to reduce congestion and the likelihood of trips. Utilise to slip mats or tape in areas prone to slips, especially during wet conditions. negularly inspect tools and equipment to ensure they are in good condition and properly stored when now use. Encourage workers to report any newly identified hazards immediately so corrective measures can be implemented. 	1L
2. Evaluate worksite	Risk of Electrical Hazards, Unsafe installation location	ЗН	 Conduct a pre-work assessment to identify any potential electrical hazards in the worksite. Ensure all workers are trained in electrical safety and aware of the specific risks associated with installing lights. Use insulated tools and equipment when working near electrical sources to minimise the risk of electric shock. Clearly mark the areas where electricity is present or being installed to warn workers and others on site. Verify that the power supply is switched off and locked out before commencing installation to prevent accidental energisation. Avoid working in wet conditions that could increase the risk of electrical shock, ensuring the area is dry before starting the task. Use personal protective equipment (PPE), such as rubber gloves and boots, designed for electrical work. Secure temporary barriers around the work area to restrict access by unauthorised personnel during installation. 	2M



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
			 Evaluate the location for safe ladder or scaffolding placement to prevent falls during installation at heights. Plan cable routing and fixture positioning away from faulty installations. 	
3. Equipment Inspection	Faulty equipment, Risk of shock from damaged lights	3H	 Conduct a thorough visual inspection of all anotrice's quipment before use to identify any visible damage, such as frayed cords or cracked casin. Ensure all electrical tools are lights have been to red and to ged by a qualified electrician within the required inspection intervals are er Australian stant ods. Use only tools are used and equalment that meet Australian safety standards and are suitable for the specific job remembers. Prohibit the coordinates or dama and equipment; tag it as "out of service" until repairs or safe disponsion between the tags. Implication a regular maintenance schedule for all electrical equipment to prevent deterioration and identify out rial faunt early. Provide portrole residual current devices (RCDs) to circuit-break electrical supply in case of fault fraction reduces shock risk. Ensure trkers are trained in proper equipment handling techniques and the correct procedures to allow into attrifying and reporting faulty equipment. Is sition lighting equipment on stable surfaces to prevent tipping over, and secure cables safely to avoid trip nazards and possible damage. Establish a clear communication process for workers to report hazards immediately which includes the identification and management of faulty equipment. Ensure all lighting installations are adequately rated for wet conditions if used outdoors, reducing the risk of electrical shock due to moisture exposure. 	2M
4. Positioning Ladder	Ladder instability, Potential for falls from height	3Н		1L



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
				1
				•
5. Dismantling old Lighting unit	Exposure to electrical hazards, Fa [*] g objects	3Н		1L



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
6. Isolating Power Supply	Risk of electric shock, Unexpected reconnection of power	4A		2M
7. Installing new Lighting Unit	Risk of falling objects, Faulty wiring	ЗН		1L



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
		1		•
8. Affixing Lights	Falls from heights, Overexertion injuries	3H		1L
				-



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
9. Replacing Wiring	Exposure to electrical hazards, incorrect wiring	ЗН		1L
10. Restoring Power Supply	Potential for short-circuiting, Electrical Fire	3H		2M



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
11. Cleaning Worksite	Potential for slips, ups, and for untidy workplace, in waste materials	F PM		1L



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
12. Operational Check	Faulty installation, Persistent Electrical Issues	2M		1L
13. Completion and Documentation	Missing or improper documentation, Miscommunication of completed task	2M		1L



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
14. Maintenance and nspection	Misidentified faults improper maintenance produures	2M		1L
15. Emergency Planning	Inadequate response to emergencies, Lack of knowledge in handling safety equipment	3H		2M



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
16. Training and Supervision	Inadequate training, Lack of proper supervision	ЗН		2M



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL
17. Personal Protective Equipment	Inadequate or incorrectuse or PPE, Lack of PPE provious	ЗH		2M
18. Regular testing and board inspections	Faulty circuits unnoticed, Inadequate inspection procedures	3H		2M



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
19. Quality Check	Misidentification of faults, Overlooked defects in light units	2M		1 L



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
20. Final documentation and Sign-off	Missed faults due dack of proper documentation, M completed tasks	2M		1L









EMERGENCY RESPONSE - CALL 000 FOR EMERGENCIES

Ensure to have an Emergency Management Plan in place as well as adequate numbers of trained first aid staff with easy access to fully stocked first aid kits, rescue equipment, material safety data sheets, adequate access to emergency communication equipment and fire-fighting equipment suitable for all classes of fire and ignition sources.

LEGISLATIVE REFERENCES

RELEVANT LEGISLATION AND CODES OF PRACTICE. DELETE THE LEGISLATIVE REFERENCES. ANY STATE OF AT ARE NOT APPLICABLE.

Queensland & Australian Capital Territory

Work Health and Safety Act 2011

Work Health and Safety Regulations 2011

Legislation QLD: https://www.worksafe.qld.gov.au/laws-and-compliance/work-health-and-safety-laws Codes of Practice QLD: https://www.worksafe.qld.gov.au/laws-and-compliance/codes-of-practice

Legislation ACT: https://www.worksafe.act.gov.au/laws-and-compliance/acts-and-regulations

Codes of Practice ACT: https://www.worksafe.act.gov.au/laws-and-compliance/codes-of-practice

New South Wales

Work Health and Safety Act 2011

Work Health and Safety Regulations 2017

Legislation NSW: https://www.safework.nsw.gov.au/legal-obligations/legislations/

Codes of Practice NSW: https://www.safework.nsw.gov.au/resource-library/lis > odes-oi racti

Northern Territory

Work Health and Safety (National Uniform Legislation) Act 2011

Work Health and Safety (National Uniform Legislation) Regulation 201

Legislation NT: https://worksafe.nt.gov.au/laws-and-compliance/wo_place-

Codes of Practice NT: https://worksafe.nt.gov.au/f

South Australia

Work Health and Safety Act 2012 (SA)

Work Health and Safety Regulations 2012 (SA)

Legislation for SA: https://www.safework.sa.gov.au/resources/le_lation

Codes of Practice for SA: https://www.safework.sa.gov.au/wor aces/codes-of-practice#COPs

Tasmania

Work Health and Safety Act 2012

Work Health and Safety (Transitional and Consequential Provisions) Act 2012

Work Health and Safety Regulations 2012

Work Health and Safety (Transitional) Regulations 2012

Legislation for TAS: https://worksafe.tas.gov.au/topics/laws-and-compliance/acts-and-regulations

Codes of Practice for TAS: https://worksafe.tas.gov.au/topics/laws-and-compliance/codes-of-practice

Details of permits, licenses or access required by regulatory bodies (add or delete as required):

- Permits from local council
- Authorisation to commence work
- Any required documents.

Victoria

Occupational Health al. Safety Act

Occupational Health and affety gulations 2017

Legis on VIC: https://www.csafe.vic.gov.au/occupational-health-and-safety-act-and-

gulat

des on actice VI autros://www.worksafe.vic.gov.au/compliance-codes-and-codes-practice

Western Australia

Work Health and Safety Act 2020

Work Health and Safety Regulations 2022

Legislation Western Australia: https://www.commerce.wa.gov.au/worksafe/legislation

Codes of Practice WA: https://www.commerce.wa.gov.au/worksafe/codes-practice

Safe Work Australia Links

Law and Regulation (All States): https://www.safeworkaustralia.gov.au/law-and-regulation Model Codes of Practice: https://www.safeworkaustralia.gov.au/resources-publications/model-codes-of-practice

Model Codes of Practice

- Managing noise and preventing hearing loss at work
- Confined spaces
- Labelling of workplace hazardous chemicals
- Managing risks of hazardous chemicals in the workplace
- Welding processes
- First aid in the workplace
- Managing the risk of falls at workplaces
- Hazardous manual tasks
- Managing the risk of falls in housing construction
- Managing electrical risks in the workplace
- Demolition work
- Excavation work
- Work health and safety consultation, cooperation and coordination
- Managing the work environment and facilities
- How to manage work health and safety risks
- Managing risks of plant in the workplace
- Construction work





SIGNATORIES OF THE SAFE WORK METHOD STATEMENT

The signed and dated personnel listed below have cooperated in the consultation and development of this Safe Work Method Statement which has been approved by the Person/s Conducting a Business or Undertaking (PCBU). In signing this Safe Work Method Statement each individual acknowledges and confirms that they have read this SWMS in full, having raised any questions for items on this Safe Work Method Statement that require clarification, and confirms that they are competent, skilled and knowledgeable for the task assigned to them. Every person acknowledges that they have received the relevant training and qualifications where required, before carrying out any work contained in this Safe Work Method Statement. By signing this Safe Work Method Statement each individual agrees to work safely, to follow any safe work instructions which are provided, and agrees to use all Personal Protective Equipment where appropriate.

Worker Name	Signature	Date

SAFE WORK IN THE STATEMENT MONITORING AND REVIEW

The SWMS must be reviewed regularly to make sure it remains a fective of must be reviewed (and revised if necessary) if relevant control measures are revised. The view process should be carried out in consultation with workers (including contractors of the SWMS and their health and safety representatives who represented that work group at the workplace.

When the SWMS has been revised the PCBU mast ensure that advised that a revision has been made and how they can access the revised SWMS, including all persons who will need to change a work procedure or system as a rest of the review are advised of the changes in a way that will enable them to implement their duties and the involved in the work must be provided with the relevant information and instruction that will assist them to understand and implement the revised SWMS.

The SWMS must be monitored regularly for the effectiveness of ensuring hazard controls are effective in reducing the risk of incidents, keeping the workplace safe for all personnel. The person responsible for monitoring the effectiveness of the Safe Work Method Statement should employ a multi-faceted approach which includes but is not limited to:

- Spot Checks.
- 2. Consultation with workers, contractors and sub-contractors.
- 3. Internal audits on a continual basis.

An approach of continuous improvement, promptly recording inconsistencies or deficiencies, followed up by immediate corrective action and consultation with all relevant personnel ensures that the PCBU is consistently developing ever-improving systems of safe work principles.

REVIEW NUMBER	1	2	3	4	5	6	7
NAME							
INITIALS							
DATE							

Version 2.5 Authorised by Review # Date of Issue: Review Date: 19





SAFE WORK METHOD STATEMENT REVIEW CHECKLIST

This Safe Work Method Statement Review Checklist is to be followed and used upon initial development of the SWMS to help ensure that all steps have been adequately taken before work commences. Think of this document as an internal audit review checklist before commencing work, and may form part of a Toolbox Talk (safety meeting) and may be used as an opportunity for education and training.

ITEMS WHICH MUST BE INCLUDED IN THE SWMS	COMPLETED	COMMENTS
The company details have been entered, including the project name and address.		
All relevant personnel consulted during the development of the SWMS.		
Name, signature, position and date signed of the person approving the SWMS.		
Specific personnel and qualifications, experience is noted in the SWMS.	7	
Provides a step-by-step process of tasks required to carry out the activity or task.		
Adequate risk assessment of any identified hazards has been completed.		
Foreseeable hazards are identified and documented for each step.		
Any hazards listed in any site risk assessments have been added to the SWMS		
SWMS initial risk (IR) column as well as residual risk (RR) column mpleted.		
Check control measures added to the SWMS are the most effective selective.		
Responsible person is assigned and listed on the person is as a person is as a person is a p		
Permit or licenses requirements specified, sur as Hot Work, Electric Work, Work at Heights etc.		
SWMS identifies plant and equipment to be us		
Details of inspection checks required for any equipment listed an inspection on the SWMS.		
Describes any mandatory qualifications, experience, and or skills required to perform the work.		
Applicable personal protective equipment is selected on the SWMS.		
Reflects and documents any legislative references and/or Australian Standards.		
Identifies any hazardous substances used with specific control measures in line with any SDS.		
REVIEWED BY	DATE REVIE	WED
SIGNATURE	DATE COMPL	ETED