



Maintenance Of Circuit Br	eakers SAFE WORK MET	HOD STATEMENT (SWMS)	
TASK OR .	ACTIVITY: Maintenance Of Circu	it Breakers	
Business Name:		ABN:	SWMS#
Business Address:			
Contact Person:	Phone:	E jil:	
THIS SAFE WORK METHOD	STATEMENT IS APPROTO BY	THE PCL OF THE ROJECT	
Under the Work Health and Safety Regulation (WHS Regulation), a person conduct the proposed work starts.	eting a business or under a (PC 1) is	required to en that a safe work method s	statement (SWMS) is prepared before
Full Name:			
Signature:	NY	Title:	Date:
Details of the person(s) responsible for ensuring implementation, monitoring	opliance the VMS a well as review	s and modifications of the SWMS.	
Full Name:		Title:	Phone:
ALL PERSONNEL PARTICIPATING IN ANY ACTIVITY ON THIS S /MS M' HAVE THE FOLLOWING COMMUNICATED	NA, 2 OF ALL RELEVANT PERSONNI EVELOPMENT AND APPROVAL OF	EL WHO HAVE BEEN CONSULTED AND CO	OMMUNICATED TO IN THE
Safety meetings or toolbox talks will be sched ed in accomply with gislative requirements to first identify any site hazards, hazards and then to further take steps to either eliminate or continuate hazard.			
If an incident or a near miss occurs, all work must sto, adately. Depending on the severity of the incident, a meeting will be called with all workers to amend the SWMS if required. The meeting may also be an educational opportunity.			
Any changes made to the SWMS after an incident or a near miss must be approved by the Person Conducting Business or Undertaking and communicated to all relevant personnel.			
The SWMS must be kept and be available for inspection at least until the work is completed. Where a SWMS is revised, all versions should be kept. If a notifiable incident occurs in relation to which the SWMS relates, then the SWMS must be kept for at least two years from the occurrence of the notifiable incident.			

Version 2.5 Authorised by Review # Date of Issue: Review Date: 1





CLIENT OR PRINCIPAL	CONTRACTOR DETAILS
Client:	SCOPE OF WORKS
Project Name:	
Project Address:	
Project Manager:	
Contact Phone:	
Date SWMS supplied to Project Manager:	
ANY HIGH BIOK CONSTRUCTOR	NAME OF THE POLIT
ANY HIGH-RISK CONSTRUCTOR	N WC & BEIN C ARIED OUT
☐ involves a risk of a person falling more than 2 meters	is carried out on or near pressurised gas mains or piping
☐ is carried out on a telecommunication tower	carried out on or near chemical, fuel or refrigerant lines
☐ involves demolition of an element of a structure that is load-bearing	\square is carried out on or near energised electrical installations or services
☐ involves demolition of an element related to the physical integral of a functure	☐ is carried out in an area that may have a contaminated or flammable atmosphere
☐ involves, or is likely to involve, disturbing asb	☐ involves tilt-up or precast concrete
☐ involves structural alteration or repair that —quires term — v sup —rt to prevent collapse	☐ is carried out on, in or adjacent to a road, railway, shipping lane or other traffic corridor
☐ is carried out in or near a confined space	☐ is carried out in an area of a workplace where there is any movement of powered mobile plant
☐ is carried out in/near a shaft or trench deeper that. tunnel involving use of explosives	☐ is carried out in areas with artificial extremes of temperature.
\square is carried out in or near water or other liquid that involves a risk of drowning.	☐ involves diving work.
ANY HIGH-RISK MACHINER	Y OR EQUIPMENT NEARBY

Version 2.5 Authorised by Review # Date of Issue: Review Date: 2



RISK MATRIX									
LIKELIHOOD	INSIGNIFICANT	MINOR	MODERATE	MAJOR	CATASTROPHIC	SCORE	ACTION	HEIRARCHY OF CONTROLS	
ALMOST CERTAIN	3 HIGH	3 HIGH	4 ACUTE	4 ACUTE	4 ACUTE	SCORE	ACTION	Elimination Remove the hazard.	
LIKELY	2 MODERATE	3 HIGH	3 HIGH	4 ACUTE	4 ACUTE	4A ACUTE	DO NOT PROCE	Substitution	
POSSIBLE	1 LOW	2 MODERATE	3 HIGH	4 ACUTE	4 ACUTE	3H HIGH	Review before work starts.	Replace the hazard.	
UNLIKELY	1 LOW	1 LOW	2 MODERATE	3 HIGH	4 ACUTE	2M MODERATE	Ensure control measures in place.	Isolate People from the hazard	
RARE	1 LOW	1 LOW	2 MODERATE	3 HIGH	3 HIGH	1L LOW	nitor and	Engineering Isolate the hazard.	
is the second m	rchy of Controls: ost effective metho nging the work is th	d of controlling a	hazard. Enginee	ering by isolati	on is the in ost e	en 'ive, while	rd. Substitution Administrative effective	Administrative Change the work. PPE	

				PERS		TIVE EQUIPM					
		Select the app	propriate PPL	abo√ ≃uitab	ic or the equi	pment used or	the job task	being perforr	ned (if applica	ıble).	
FOOT PROTECTION	HAND PROTECTION	HEAD PROTECTION	HEARING ETION	P ECTION	R PIRATORY PROTECTION	FACE PROTECTION	HIGH-VIS CLOTHING	PROTECTIVE CLOTHING	FALL PROTECTION	SUN PROTECTION	HAIR/JEWELLERY SECURED
Other PPE R	Required:										
	Pe	ermit or Licen	ses Requirem	ents		Mandatory Qualifications and Training					



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
1. Preparation	Electrical shock, manual handling injuries	3H	 Conduct a pre-work safety briefing to discretaine task and potential hazards. Ensure all personnel are trained and compount in elevatical work and manual handling techniques. De-energise and isolate the circuit breaker be accommending maintenance work. Use lockout/tagout procedulate to prevent accide at leneral ation of equipment. Verify absence of water using appropriate testing access before starting work. Wear appropriate person a proteon a equipment fincluding insulated gloves and eye protection. Use insulate abols specifically design the electrical work to reduce the risk of shock. Plalace qual handling asks in advance to avoid awkward postures and overexertion. Utilis mananical ting aids such as trolleys or hoists for moving heavy components. Maintain a conning anised work area to minimise tripping and other physical hazards. Simploying but a system, ensuring that at least two personnel are present during electrical work. Ensural equate lighting in the work environment to improve visibility and reduce errors. Istablish an emergency response plan in case of electrical incidents. Full assess risks and update control measures regularly as part of continuous improvement efforts. 	2M
2. Inspection of the circuit breaker	Unexpected energy release, exposure to harmful substances	ЗН	 Conduct a thorough risk assessment before beginning the inspection process to identify potential hazards and plan appropriate control measures. Ensure all personnel involved are trained in electrical safety and circuit breaker maintenance procedures. Isolate the circuit breaker from all potential energy sources and ensure it is locked out and tagged to prevent accidental energisation. Use insulated tools and personal protective equipment (PPE) such as rubber gloves, face shields, and arc-rated clothing to minimise the risk of electrical shock or burns. Verify that the circuit breaker is effectively de-energised using appropriate testing equipment before commencing inspection activities. Deploy barriers or signage around the work area to alert others to the ongoing maintenance activity and prevent unauthorised access. Implement proper ventilation when working in areas where exposure to harmful substances or gases might occur. Keep a safe distance from any components identified as containing or potentially releasing hazardous substances. 	1L



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
			- Ensure that emergency contact information and first aid resources are readily available in case of an incident.	
			- Use appropriate cleaning agents and methods to sold generating airborne toxic substances during inspection or cleaning of components.	
			- Regularly inspect PPE and equipment for this of wear damage and replace them as necessary to maintain effectiveness.	
			- Maintain clear communication between team it in the between the activities safely.	
			- Have a standby person with knowledge of electrical comes present to provide assistance or call for help if needed.	
			- Documents a report any cidents unexpressed conditions encountered during the inspection to facilitate continuous improvement in such cactices.	
			- Enst > persol (are trained and competent in electrical safety procedures.	
			- Verify he a puit break r is correctly identified and labeled before isolation.	
			Use log put/tage ut (LOTO) procedures to prevent unintended activation.	
			- Charly a mmunicate and document the isolation process with all team members.	
		\	Utilize a, ropriate Personal Protective Equipment (PPE), such as insulated gloves and face shields.	
			- t for absence of voltage using a suitable testing device before commencing work.	
2 looloting the circuit			Display safety signage indicating electrical work in progress to deter unauthorized access.	
Isolating the circuit breaker	Unintended activation, electrical shock	4A	- Assign a team member to act as a safety observer during the isolation process.	2M
			- Maintain clear and open communication with other departments that may be affected by the isolation.	
			- Implement a buddy system to ensure tasks are performed safely and under supervision.	
			- Regularly inspect and maintain isolation equipment to ensure reliability.	
			- Confirm that de-energized equipment is grounded to protect against residual charges.	
			- Conduct a risk assessment prior to isolation to identify potential hazards and required controls.	
			- Develop an emergency response plan specifically for electrical incidents, ensuring all personnel are familiar with it.	
4. Application of lockout	Ineffective communication, lockout	3H		1L
tagout	tagout errors			



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
5. Removal of circuit breaker cover	Sharp objects, slipped tool injuries	2M		1L



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
. Visual check of ternal parts	Improper lighting, assed defects	2M		1L



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
JOB STEP SPECIFIC WORK STEPS	POTENTIAL HAZARDS HAZARDS THAT MAY ARISE	IR INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RR RESIDUAL RISK
8. Cleaning internal parts with approved cleaning solvents	Chemical hazards, fume exposure	2M		1L



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
9. Replacing defective parts	Incorrect installation, unavailability specific tools	2M		1L



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
10. Replacement of circuit breaker cover	Pinching accidents, incorrect fastening	2M		1L
11. De-energise and tie off circuit breaker	Residual energy, improper de-energising	ЗН		1L



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
				•
				_
	Incomplete tests, incorre, result			_
12. Verification Test	Incomplete tests, incorrequestion	2M		1L



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS		RESIDUAL RISK
13. Recording of results and documentation	Information loss/misinterpretation, unreported anomalies	2M		I 1L
14. Cleanup and disposal operations	Chemical exposure, wrong disposal method	2M		1L



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
15. Removal of lockout tagout and restoration of system	Unintentional re-energisation, lockout tagout errors	ЗН		2M



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
16. Post-maintenance checks and tests	Missed defects, incorrect results interpretation	2M		1L
17. Handover and briefing of maintenance reports	Incomplete information transfer, miscommunication	1L		1L









EMERGENCY RESPONSE - CALL 000 FOR EMERGENCIES

Ensure to have an Emergency Management Plan in place as well as adequate numbers of trained first aid staff with easy access to fully stocked first aid kits, rescue equipment, material safety data sheets, adequate access to emergency communication equipment and fire-fighting equipment suitable for all classes of fire and ignition sources.

LEGISLATIVE REFERENCES

RELEVANT LEGISLATION AND CODES OF PRACTICE. DELETE THE LEGISLATIVE REFERENCES. ANY STATE OF AT ARE NOT APPLICABLE.

Queensland & Australian Capital Territory

Work Health and Safety Act 2011

Work Health and Safety Regulations 2011

 $\textbf{Legislation QLD:} \ \underline{\textbf{https://www.worksafe.qld.gov.au/laws-and-compliance/work-health-and-safety-laws}$

Codes of Practice QLD: https://www.worksafe.qld.gov.au/laws-and-compliance/codes-of-practice Legislation ACT: https://www.worksafe.act.gov.au/laws-and-compliance/acts-and-regulations

Codes of Practice ACT: https://www.worksafe.act.gov.au/laws-and-compliance/codes-of-practice

New South Wales

Work Health and Safety Act 2011

Work Health and Safety Regulations 2017

Legislation NSW: https://www.safework.nsw.gov.au/legal-obligations/legislative

Codes of Practice NSW: https://www.safework.nsw.gov.au/resource-library/lis > odes-oi racti

Northern Territory

Work Health and Safety (National Uniform Legislation) Act 2011

Work Health and Safety (National Uniform Legislation) Regulation 201

Legislation NT: https://worksafe.nt.gov.au/laws-and-compliance/wo_place-

Codes of Practice NT: https://worksafe.nt.gov.au/f

South Australia

Work Health and Safety Act 2012 (SA)

Work Health and Safety Regulations 2012 (SA)

Legislation for SA: https://www.safework.sa.gov.au/resources/legislation

Codes of Practice for SA: https://www.safework.sa.gov.au/work_aces/codes-of-practice#COPs

Tasmania

Work Health and Safety Act 2012

Work Health and Safety (Transitional and Consequential Provisions) Act 2012

Work Health and Safety Regulations 2012

Work Health and Safety (Transitional) Regulations 2012

Legislation for TAS: https://worksafe.tas.gov.au/topics/laws-and-compliance/acts-and-regulations

Codes of Practice for TAS: https://worksafe.tas.gov.au/topics/laws-and-compliance/codes-of-practice

Details of permits, licenses or access required by regulatory bodies (add or delete as required):

- Permits from local council
- Authorisation to commence work
- Any required documents.

Victoria

Occupational Health al. Safety Act

Occupational Health and affety gulations 2017

Legis on VIC: https://www.csafe.vic.gov.au/occupational-health-and-safety-act-and-

gulat

des on actice VI autros://www.worksafe.vic.gov.au/compliance-codes-and-codes-practice

Western Australia

Work Health and Safety Act 2020

Work Health and Safety Regulations 2022

Legislation Western Australia: https://www.commerce.wa.gov.au/worksafe/legislation

Codes of Practice WA: https://www.commerce.wa.gov.au/worksafe/codes-practice

Safe Work Australia Links

Law and Regulation (All States): https://www.safeworkaustralia.gov.au/law-and-regulation Model Codes of Practice: https://www.safeworkaustralia.gov.au/resources-publications/model-codes-of-practice

Model Codes of Practice

- Managing noise and preventing hearing loss at work
- Confined spaces
- Labelling of workplace hazardous chemicals
- Managing risks of hazardous chemicals in the workplace
- Welding processes
- First aid in the workplace
- Managing the risk of falls at workplaces
- Hazardous manual tasks
- Managing the risk of falls in housing construction
- Managing electrical risks in the workplace
- Demolition work
- Excavation work
- Work health and safety consultation, cooperation and coordination
- Managing the work environment and facilities
- How to manage work health and safety risks
- Managing risks of plant in the workplace
- Construction work





SIGNATORIES OF THE SAFE WORK METHOD STATEMENT

The signed and dated personnel listed below have cooperated in the consultation and development of this Safe Work Method Statement which has been approved by the Person/s Conducting a Business or Undertaking (PCBU). In signing this Safe Work Method Statement each individual acknowledges and confirms that they have read this SWMS in full, having raised any questions for items on this Safe Work Method Statement that require clarification, and confirms that they are competent, skilled and knowledgeable for the task assigned to them. Every person acknowledges that they have received the relevant training and qualifications where required, before carrying out any work contained in this Safe Work Method Statement. By signing this Safe Work Method Statement each individual agrees to work safely, to follow any safe work instructions which are provided, and agrees to use all Personal Protective Equipment where appropriate.

Worker Name	Signature	Date

SAFE WORK IN THE STATEMENT MONITORING AND REVIEW

The SWMS must be reviewed regularly to make sure it remains a fective of must be reviewed (and revised if necessary) if relevant control measures are revised. The view results should be carried out in consultation with workers (including contractors as use intractors) the may be cated by the operation of the SWMS and their health and safety representatives who represented that work group at the workplace.

When the SWMS has been revised the PCBU mast ensure that advised that a revision has been made and how they can access the revised SWMS, including all persons who will need to change a work procedure or system as a rest of the review are advised of the changes in a way that will enable them to implement their duties and the involved in the work must be provided with the relevant information and instruction that will assist them to understand and implement the revised SWMS.

The SWMS must be monitored regularly for the effectiveness of ensuring hazard controls are effective in reducing the risk of incidents, keeping the workplace safe for all personnel. The person responsible for monitoring the effectiveness of the Safe Work Method Statement should employ a multi-faceted approach which includes but is not limited to:

- Spot Checks.
- 2. Consultation with workers, contractors and sub-contractors.
- 3. Internal audits on a continual basis.

An approach of continuous improvement, promptly recording inconsistencies or deficiencies, followed up by immediate corrective action and consultation with all relevant personnel ensures that the PCBU is consistently developing ever-improving systems of safe work principles.

REVIEW NUMBER	1	2	3	4	5	6	7
NAME							
INITIALS							
DATE							

Version 2.5 Authorised by Review # Date of Issue: Review Date: 18





SAFE WORK METHOD STATEMENT REVIEW CHECKLIST

This Safe Work Method Statement Review Checklist is to be followed and used upon initial development of the SWMS to help ensure that all steps have been adequately taken before work commences. Think of this document as an internal audit review checklist before commencing work, and may form part of a Toolbox Talk (safety meeting) and may be used as an opportunity for education and training.

ITEMS WHICH MUST BE INCLUDED IN THE SWMS	COMPLETED	COMMENTS
The company details have been entered, including the project name and address.		
All relevant personnel consulted during the development of the SWMS.		
Name, signature, position and date signed of the person approving the SWMS.		
Specific personnel and qualifications, experience is noted in the SWMS.	7	
Provides a step-by-step process of tasks required to carry out the activity or task.		
Adequate risk assessment of any identified hazards has been completed.		
Foreseeable hazards are identified and documented for each step.		
Any hazards listed in any site risk assessments have been added to the SWMS		
SWMS initial risk (IR) column as well as residual risk (RR) column ppleted.		
Check control measures added to the SWMS are the most effective selections		
Responsible person is assigned and listed on the part the important portrol measures.		
Permit or licenses requirements specified, sur as Hot Work, Electric Work, Work at Heights etc.		
SWMS identifies plant and equipment to be us		
Details of inspection checks required for any equipment listed a noted on the SWMS.		
Describes any mandatory qualifications, experience, a g or skills required to perform the work.		
Applicable personal protective equipment is selected on the SWMS.		
Reflects and documents any legislative references and/or Australian Standards.		
Identifies any hazardous substances used with specific control measures in line with any SDS.		
REVIEWED BY	DATE REVIE	WED
SIGNATURE	DATE COMPL	ETED