

## Mechanical Services Switchboard Work | SAFE WORK METHOD STATEMENT (SWMS)

### TASK OR ACTIVITY: Mechanical Services Switchboard Work

Business Name:	ABN:	SWMS#
Business Address:		
Contact Person:	Phone:	Email:

### THIS SAFE WORK METHOD STATEMENT IS APPROVED BY THE PCBU OF THE PROJECT

Under the Work Health and Safety Regulation (WHS Regulation), a person conducting a business or undertaking (PCBU) is required to ensure that a safe work method statement (SWMS) is prepared before the proposed work starts.

Full Name:		
Signature:	Title:	Date:
Details of the person(s) responsible for ensuring implementation, monitoring compliance of the SWMS as well as reviews and modifications of the SWMS.		
Full Name:	Title:	Phone:

### ALL PERSONNEL PARTICIPATING IN ANY ACTIVITY ON THIS SWMS MUST HAVE THE FOLLOWING COMMUNICATED

Safety meetings or toolbox talks will be scheduled in accordance with legislative requirements to first identify any site hazards, then to communicate those hazards and then to further take steps to either eliminate or control each hazard.

If an incident or a near miss occurs, all work must stop immediately. Depending on the severity of the incident, a meeting will be called with all workers to amend the SWMS if required. The meeting may also be an educational opportunity.

Any changes made to the SWMS after an incident or a near miss must be approved by the Person Conducting Business or Undertaking and communicated to all relevant personnel.

The SWMS must be kept and be available for inspection at least until the work is completed. Where a SWMS is revised, all versions should be kept. If a notifiable incident occurs in relation to which the SWMS relates, then the SWMS must be kept for at least two years from the occurrence of the notifiable incident.

### NAME OF ALL RELEVANT PERSONNEL WHO HAVE BEEN CONSULTED AND COMMUNICATED TO IN THE DEVELOPMENT AND APPROVAL OF THIS SWMS

### CLIENT OR PRINCIPAL CONTRACTOR DETAILS

Client:	SCOPE OF WORKS
Project Name:	
Project Address:	
Project Manager:	
Contact Phone:	
Date SWMS supplied to Project Manager:	

### ANY HIGH-RISK CONSTRUCTION WORK BEING CARRIED OUT

- |  |  |
|--|--|
| <input type="checkbox"/> involves a risk of a person falling more than 2 meters  | <input type="checkbox"/> is carried out on or near pressurised gas mains or piping                                     |
| <input type="checkbox"/> is carried out on a telecommunication tower   | <input type="checkbox"/> is carried out on or near chemical, fuel or refrigerant lines                                 |
| <input type="checkbox"/> involves demolition of an element of a structure that is load-bearing                           | <input type="checkbox"/> is carried out on or near energised electrical installations or services                      |
| <input type="checkbox"/> involves demolition of an element related to the physical integrity of a structure              | <input type="checkbox"/> is carried out in an area that may have a contaminated or flammable atmosphere                |
| <input type="checkbox"/> involves, or is likely to involve, disturbing asbestos  | <input type="checkbox"/> involves tilt-up or precast concrete  |
| <input type="checkbox"/> involves structural alteration or repair that requires temporary support to prevent collapse    | <input type="checkbox"/> is carried out on, in or adjacent to a road, railway, shipping lane or other traffic corridor |
| <input type="checkbox"/> is carried out in or near a confined space  | <input type="checkbox"/> is carried out in an area of a workplace where there is any movement of powered mobile plant  |
| <input type="checkbox"/> is carried out in/near a shaft or trench deeper than 1.5m or tunnel involving use of explosives | <input type="checkbox"/> is carried out in areas with artificial extremes of temperature.                              |
| <input type="checkbox"/> is carried out in or near water or other liquid that involves a risk of drowning.               | <input type="checkbox"/> involves diving work.   |

### ANY HIGH-RISK MACHINERY OR EQUIPMENT NEARBY

RISK MATRIX									
LIKELIHOOD	INSIGNIFICANT	MINOR	MODERATE	MAJOR	CATASTROPHIC	SCORE	ACTION	HEIRARCHY OF CONTROLS	
ALMOST CERTAIN	3 HIGH	3 HIGH	4 ACUTE	4 ACUTE	4 ACUTE			 <p><b>Elimination</b> Remove the hazard.</p> <p><b>Substitution</b> Replace the hazard.</p> <p><b>Isolation</b> Isolate People from the hazard</p> <p><b>Engineering</b> Isolate the hazard.</p> <p><b>Administrative</b> Change the work.</p> <p><b>PPE</b></p>	
LIKELY	2 MODERATE	3 HIGH	3 HIGH	4 ACUTE	4 ACUTE	4A ACUTE	DO NOT PROCEED		
POSSIBLE	1 LOW	2 MODERATE	3 HIGH	4 ACUTE	4 ACUTE	3H HIGH	Review before work starts.		
UNLIKELY	1 LOW	1 LOW	2 MODERATE	3 HIGH	4 ACUTE	2M MODERATE	Ensure control measures in place.		
RARE	1 LOW	1 LOW	2 MODERATE	3 HIGH	3 HIGH	1L LOW	Monitor and keep records		

**Notes on Hierarchy of Controls:** Elimination methods are the most effective and preferred when controlling a hazard. Substitution is the second most effective method of controlling a hazard. Engineering by isolation is the third most effective, while Administrative Controls by changing the work is the fourth most effective method. PPE (Personal Protective Equipment) is the least effective method.

PERSONAL PROTECTIVE EQUIPMENT (PPE)											
Select the appropriate PPE above suitable for the equipment used or the job task being performed (if applicable).											
FOOT PROTECTION	HAND PROTECTION	HEAD PROTECTION	HEARING PROTECTION	EYE PROTECTION	RESPIRATORY PROTECTION	FACE PROTECTION	HIGH-VIS CLOTHING	PROTECTIVE CLOTHING	FALL PROTECTION	SUN PROTECTION	HAIR/JEWELLERY SECURED
											
<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
Other PPE Required:											
Permit or Licenses Requirements						Mandatory Qualifications and Training					

JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
1. Preparation	Exposure to live electrical parts, Incorrect handling of tools	3H	<ul style="list-style-type: none"> <li>- Conduct a thorough risk assessment before starting work to identify any potential hazards.</li> <li>- Ensure all workers are trained and competent in electrical safety and the use of mechanical services switchboards.</li> <li>- Verify that the switchboard is de-energised before beginning any maintenance or installation work.</li> <li>- Use lockout/tagout procedures to secure all energy sources and prevent accidental re-energisation.</li> <li>- Wear appropriate personal protective equipment (PPE), including insulating gloves, safety goggles, and flame-resistant clothing.</li> <li>- Utilise insulated tools when working close to live electrical parts to minimise the risk of electric shock.</li> <li>- Implement exclusion zones around live parts, marked with clear signage and barriers to warn and protect workers.</li> <li>- Employ a standby person, knowledgeable in emergency response, to monitor the work area and assist if needed.</li> <li>- Inspect all tools and equipment for damage before use to ensure they are in safe working condition.</li> <li>- Utilise electrically approved ladders made of non-conductive materials, like fibreglass, instead of metal ladders.</li> <li>- Establish clear communication protocols among team members to co-ordinate activities safely.</li> <li>- Ensure adequate lighting is available to properly illuminate the workspace and reduce the chances of mishandling tools.</li> <li>- Continuously monitor environmental conditions, such as weather, which could increase risks when working outdoors.</li> <li>- Store and handle tools securely to prevent them from becoming projectiles or causing trips and falls.</li> </ul>	2M
2. Equipment setup	Tripping over equipment, Electrocution	3H	<ul style="list-style-type: none"> <li>- Conduct a pre-start meeting to discuss the placement of equipment and walkway paths to prevent tripping hazards.</li> <li>- Use insulated mats and gloves when setting up equipment near live electrical parts to reduce the risk of electrocution.</li> <li>- Keep all cables and cords neatly organised and away from walkways to minimise tripping risks.</li> <li>- Place visible warning signs around areas with potential electrical hazards to alert workers.</li> <li>- Ensure that all electrical equipment is tested and tagged in accordance with Australian standards before use.</li> <li>- Assign a competent person to supervise equipment setup and ensure adherence to safety protocols.</li> <li>- Implement barricades or barriers around high-risk areas to prevent unauthorised access during equipment setup.</li> </ul>	2M

JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
			<ul style="list-style-type: none"> <li>- Provide adequate lighting in areas where the switchboard equipment is being set up to enhance visibility and detection of hazards.</li> <li>- Ensure all workers involved in the setup are trained in recognising and mitigating electrical and tripping hazards.</li> <li>- Have an emergency response plan in place including first aid and fire extinguisher accessibility, in case of any incidents during setup.</li> </ul>	
3. Isolating the power	Incorrect isolation process, Electrocution	4H	<ul style="list-style-type: none"> <li>- Conduct a pre-work risk assessment to identify potential hazards related to power isolation.</li> <li>- Ensure all workers involved are trained in lockout/tagout procedures and electrical safety standards.</li> <li>- Verify that the correct switchboard and circuit are identified for isolation.</li> <li>- Use properly maintained and tested personal protective equipment (PPE) such as rubber gloves, insulated boots, safety glasses, and arc flash clothing.</li> <li>- Employ an approved lockout/tagout kit with unique locks and tags for each worker involved.</li> <li>- Confirm that the latest electrical drawings and schematics are available and consulted to correctly identify isolation points.</li> <li>- Utilize multi-step verification by having more than one person check the isolation procedure before beginning work.</li> <li>- Follow standard operating procedures for de-energising circuits, ensuring adherence to established guidelines.</li> <li>- Carry out a test for voltage absence using a calibrated and approved voltage tester before starting any work on the switchboard.</li> <li>- Implement a communication protocol ensuring clear instructions are given and confirmed among team members regarding the isolation process.</li> <li>- Display warning signs and barriers around the work area to prevent unauthorised access during the isolation process.</li> <li>- Maintain an emergency response plan that includes contact details of emergency services and first-aid measures for electrocution incidents.</li> <li>- Perform a post-isolation inspection to verify thorough implementation of all safety controls and secure locking mechanism.</li> <li>- Document each step of the isolation process, including date, time, personnel involved, and equipment isolated, to ensure traceability and compliance.</li> </ul>	2M
4. Switchboard inspection	Sharp objects, High temperature exposure	3H	<div></div> <div></div>	1L



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
			<div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div>	
6. Replace faulty parts	Hand injuries, Exposure to harmful substances	3H	<div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div>	2M

Exploración de la propiedad intelectual

4A



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
			<div>SAMPLE</div> <div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> </div>	
9. Clean up area	Slips, trips, and falls, Cuts or skin puncture	3H	<div>SAMPLE</div> <div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> </div>	1L

JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
10. Documenting work	Miscommunication leading to mistakes, Paper cuts	2M	<div>SAMPLE</div>	1L
11. Switchboard reassembling	Finger trapping, Electric shock	4A		2M

[illegible]

JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
13. Post-operation testing	Electric shock, equipment malfunction	4A		2M
14. System handover	Incorrect system operation leading to injury	3H		2M

JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
			<div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div>	
15. Maintenance Brief	Misunderstanding instructions, Mental stress	2M	<div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div>	1L

JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
16. Switchboard decommissioning	Exposure to hazardous material, Hand injuries	3H		2M
17. Material disposal	Injury from sharp objects, exposure to harmful substances	3H		2M

JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
			<div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div>	
18. Final Clean-Up	Slips, trips and falls, Cuts or skin puncture	3H	<div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div> <div></div>	1L

[illegible]





## EMERGENCY RESPONSE – CALL 000 FOR EMERGENCIES

Ensure to have an Emergency Management Plan in place as well as adequate numbers of trained first aid staff with easy access to fully stocked first aid kits, rescue equipment, material safety data sheets, adequate access to emergency communication equipment and fire-fighting equipment suitable for all classes of fire and ignition sources.

## LEGISLATIVE REFERENCES

RELEVANT LEGISLATION AND CODES OF PRACTICE. DELETE THE LEGISLATIVE REFERENCES IF ANY STATE THAT ARE NOT APPLICABLE

### Queensland & Australian Capital Territory

Work Health and Safety Act 2011

Work Health and Safety Regulations 2011

Legislation QLD: <https://www.worksafe.qld.gov.au/laws-and-compliance/work-health-and-safety-laws>

Codes of Practice QLD: <https://www.worksafe.qld.gov.au/laws-and-compliance/codes-of-practice>

Legislation ACT: <https://www.worksafe.act.gov.au/laws-and-compliance/acts-and-regulations>

Codes of Practice ACT: <https://www.worksafe.act.gov.au/laws-and-compliance/codes-of-practice>

### Victoria

Occupational Health and Safety Act 2004

Occupational Health and Safety Regulations 2017

Legislation VIC: <https://www.worksafe.vic.gov.au/occupational-health-and-safety-act-and-regulations>

Codes of Practice VIC: <https://www.worksafe.vic.gov.au/compliance-codes-and-codes-practice>

### New South Wales

Work Health and Safety Act 2011

Work Health and Safety Regulations 2017

Legislation NSW: <https://www.safework.nsw.gov.au/legal-obligations/legislation>

Codes of Practice NSW: <https://www.safework.nsw.gov.au/resource-library/list-codes-of-practice>

### Western Australia

Work Health and Safety Act 2020

Work Health and Safety Regulations 2022

Legislation Western Australia: <https://www.commerce.wa.gov.au/worksafe/legislation>

Codes of Practice WA: <https://www.commerce.wa.gov.au/worksafe/codes-practice>

### Northern Territory

Work Health and Safety (National Uniform Legislation) Act 2011

Work Health and Safety (National Uniform Legislation) Regulations 2011

Legislation NT: <https://worksafe.nt.gov.au/laws-and-compliance/workplace-safety-laws>

Codes of Practice NT: <https://worksafe.nt.gov.au/laws-and-compliance/codes-of-practice>

### Safe Work Australia Links

Law and Regulation (All States): <https://www.safeworkaustralia.gov.au/law-and-regulation>

Model Codes of Practice: <https://www.safeworkaustralia.gov.au/resources-publications/model-codes-of-practice>

### Model Codes of Practice

- Managing noise and preventing hearing loss at work
- Confined spaces
- Labelling of workplace hazardous chemicals
- Managing risks of hazardous chemicals in the workplace
- Welding processes
- First aid in the workplace
- Managing the risk of falls at workplaces
- Hazardous manual tasks
- Managing the risk of falls in housing construction
- Managing electrical risks in the workplace
- Demolition work
- Excavation work
- Work health and safety consultation, cooperation and coordination
- Managing the work environment and facilities
- How to manage work health and safety risks
- Managing risks of plant in the workplace
- Construction work

### South Australia

Work Health and Safety Act 2012 (SA)

Work Health and Safety Regulations 2012 (SA)

Legislation for SA: <https://www.safework.sa.gov.au/resources/legislation>

Codes of Practice for SA: <https://www.safework.sa.gov.au/workplaces/codes-of-practice#COPs>

### Tasmania

Work Health and Safety Act 2012

Work Health and Safety (Transitional and Consequential Provisions) Act 2012

Work Health and Safety Regulations 2012

Work Health and Safety (Transitional) Regulations 2012

Legislation for TAS: <https://worksafe.tas.gov.au/topics/laws-and-compliance/acts-and-regulations>

Codes of Practice for TAS: <https://worksafe.tas.gov.au/topics/laws-and-compliance/codes-of-practice>

Details of permits, licenses or access required by regulatory bodies (add or delete as required):

- Permits from local council
- Authorisation to commence work
- Any required documents.

## SIGNATORIES OF THE SAFE WORK METHOD STATEMENT

The signed and dated personnel listed below have cooperated in the consultation and development of this Safe Work Method Statement which has been approved by the Person/s Conducting a Business or Undertaking (PCBU). In signing this Safe Work Method Statement each individual acknowledges and confirms that they have read this SWMS in full, having raised any questions for items on this Safe Work Method Statement that require clarification, and confirms that they are competent, skilled and knowledgeable for the task assigned to them. Every person acknowledges that they have received the relevant training and qualifications where required, before carrying out any work contained in this Safe Work Method Statement. By signing this Safe Work Method Statement each individual agrees to work safely, to follow any safe work instructions which are provided, and agrees to use all Personal Protective Equipment where appropriate.

Worker Name	Signature	Date

## SAFE WORK METHOD STATEMENT MONITORING AND REVIEW

**The SWMS must be reviewed regularly** to make sure it remains effective and must be reviewed (and revised if necessary) if relevant control measures are revised. The review must be carried out in consultation with workers (including contractors and sub-contractors) who may be affected by the operation of the SWMS and their health and safety representatives who represent that work group at the workplace.

When the SWMS has been revised the PCBU must ensure that all persons involved with the work are advised that a revision has been made and how they can access the revised SWMS, including all persons who will need to change a work procedure or system as a result of the review are advised of the changes in a way that will enable them to implement their duties consistently with the revised SWMS. All workers that will be involved in the work must be provided with the relevant information and instruction that will assist them to understand and implement the revised SWMS.

**The SWMS must be monitored regularly** for the effectiveness of ensuring hazard controls are effective in reducing the risk of incidents, keeping the workplace safe for all personnel. The person responsible for monitoring the effectiveness of the Safe Work Method Statement should employ a multi-faceted approach which includes but is not limited to:

1. Spot Checks.
2. Consultation with workers, contractors and sub-contractors.
3. Internal audits on a continual basis.

An approach of continuous improvement, promptly recording inconsistencies or deficiencies, followed up by immediate corrective action and consultation with all relevant personnel ensures that the PCBU is consistently developing ever-improving systems of safe work principles.

REVIEW NUMBER	1	2	3	4	5	6	7
NAME							
INITIALS							
DATE							

## SAFE WORK METHOD STATEMENT REVIEW CHECKLIST

This Safe Work Method Statement Review Checklist is to be followed and used upon initial development of the SWMS to help ensure that all steps have been adequately taken before work commences. Think of this document as an internal audit review checklist before commencing work, and may form part of a Toolbox Talk (safety meeting) and may be used as an opportunity for education and training.

ITEMS WHICH MUST BE INCLUDED IN THE SWMS	COMPLETED	COMMENTS
The company details have been entered, including the project name and address.	<input checked="" type="checkbox"/>	
All relevant personnel consulted during the development of the SWMS.	<input checked="" type="checkbox"/>	
Name, signature, position and date signed of the person approving the SWMS.	<input type="checkbox"/>	
Specific personnel and qualifications, experience is noted in the SWMS.	<input checked="" type="checkbox"/>	
Provides a step-by-step process of tasks required to carry out the activity or task.	<input checked="" type="checkbox"/>	
Adequate risk assessment of any identified hazards has been completed.	<input checked="" type="checkbox"/>	
Foreseeable hazards are identified and documented for each step.	<input checked="" type="checkbox"/>	
Any hazards listed in any site risk assessments have been added to the SWMS.	<input checked="" type="checkbox"/>	
SWMS initial risk (IR) column as well as residual risk (RR) column completed.	<input checked="" type="checkbox"/>	
Check control measures added to the SWMS are the most effective selected.	<input checked="" type="checkbox"/>	
Responsible person is assigned and listed on the SWMS for the implementation of control measures.	<input checked="" type="checkbox"/>	
Permit or licenses requirements specified, such as Hot Work, Electrical Work, Work at Heights etc.	<input checked="" type="checkbox"/>	
SWMS identifies plant and equipment to be used.	<input checked="" type="checkbox"/>	
Details of inspection checks required for any equipment listed as noted on the SWMS.	<input checked="" type="checkbox"/>	
Describes any mandatory qualifications, experience, training or skills required to perform the work.	<input checked="" type="checkbox"/>	
Applicable personal protective equipment is selected on the SWMS.	<input checked="" type="checkbox"/>	
Reflects and documents any legislative references and/or Australian Standards.	<input checked="" type="checkbox"/>	
Identifies any hazardous substances used with specific control measures in line with any SDS.	<input checked="" type="checkbox"/>	
REVIEWED BY		
SIGNATURE		
DATE REVIEWED		
DATE COMPLETED		