



Overhead Power and External Electri	ical Infrastructure   SAFE V	VORK METHOD STATEMENT	(SWMS)
TASK OR ACTIVITY:	Overhead Power and External El	ectrical Infrastructure	
Business Name:		ABN:	SWMS#
Business Address:			
Contact Person:	Phone:	E ail:	
THIS SAFE WORK METHOD	STATEMENT IS APPROVED BY	THE PCL OF THE ROJECT	
Under the Work Health and Safety Regulation (WHS Regulation), a person conduct the proposed work starts.	cting a business or undo	required to er. sthat a safe work method s	statement (SWMS) is prepared before
Full Name:			
Signature:		Title:	Date:
Details of the person(s) responsible for ensuring implementation, monitoring	roliance the VMS a well as review	s and modifications of the SWMS.	
Full Name:		Title:	Phone:
ALL PERSONNEL PARTICIPATING IN ANY ACTIVITY ON THIS 5 MS M HAVE THE FOLLOWING COMMUNICATED	NALE OF ALL RELEVANT PERSONN EVELOPMENT AND APPROVAL OF	EL WHO HAVE BEEN CONSULTED AND CO THIS SWMS	OMMUNICATED TO IN THE
Safety meetings or toolbox talks will be scheded in accomply with gislative requirements to first identify any site hazards, and then to further take steps to either eliminate or continuous each hazard.			
If an incident or a near miss occurs, all work must sto, quately. Depending on the severity of the incident, a meeting will be called with all workers to amend the SWMS if required. The meeting may also be an educational opportunity.			
Any changes made to the SWMS after an incident or a near miss must be approved by the Person Conducting Business or Undertaking and communicated to all relevant personnel.			
The SWMS must be kept and be available for inspection at least until the work is completed. Where a SWMS is revised, all versions should be kept. If a notifiable incident occurs in relation to which the SWMS relates, then the SWMS must be kept for at least two years from the occurrence of the notifiable incident.			

Version 2.5 Authorised by Review # Date of Issue: Review Date: 1





CLIENT OR PRINCIPAL	CONTRACTOR DETAILS
Client:	SCOPE OF WORKS
Project Name:	
Project Address:	
Project Manager:	
Contact Phone:	
Date SWMS supplied to Project Manager:	
ANY HIGH-RISK CONSTRUCTO	ON WO K BEIN O KRIED OUT
☐ involves a risk of a person falling more than 2 meters	☐ is carried out on or near pressurised gas mains or piping
☐ is carried out on a telecommunication tower	carried out on or near chemical, fuel or refrigerant lines
☐ involves demolition of an element of a structure that is load-bearing	☐ is carried out on or near energised electrical installations or services
☐ involves demolition of an element related to the physical integration of a ructure	☐ is carried out in an area that may have a contaminated or flammable atmosphere
☐ involves, or is likely to involve, disturbing asb	☐ involves tilt-up or precast concrete
☐ involves structural alteration or repair that — quires term — ov sup — rt to prevent collapse	☐ is carried out on, in or adjacent to a road, railway, shipping lane or other traffic corridor
is carried out in or near a confined space	☐ is carried out in an area of a workplace where there is any movement of powered mobile plant
☐ is carried out in/near a shaft or trench deeper tha tunnel involving use of explosives	☐ is carried out in areas with artificial extremes of temperature.
☐ is carried out in or near water or other liquid that involves a risk of drowning.	☐ involves diving work.
ANY HIGH-RISK MACHINER	RY OR EQUIPMENT NEARBY

Version 2.5 Authorised by Review # Date of Issue: Review Date: 2



RISK MATRIX											
LIKELIHOOD	INSIGNIFICANT	MINOR	MODERATE	MAJOR	CATASTROPHIC	SCOBE	ACTION		HEIRARCHY OF CONTROLS		
ALMOST CERTAIN	3 HIGH	3 HIGH	4 ACUTE	4 ACUTE	4 ACUTE	SCORE ACTION	4	ACTION		Elimination Remove the hazard.	
LIKELY	2 MODERATE	3 HIGH	3 HIGH	4 ACUTE	4 ACUTE	4A ACUTE	DO NOT PROCE		Substitution		
POSSIBLE	1 LOW	2 MODERATE	3 HIGH	4 ACUTE	4 ACUTE	3H HIGH	Review befor work starts.		Replace the hazard.		
UNLIKELY	1 LOW	1 LOW	2 MODERATE	3 HIGH	4 ACUTE	2M MODERATE	Ensure control measures in place.		Isolate People from the hazard		
RARE	1 LOW	1 LOW	2 MODERATE	3 HIGH	3 HIGH	1L LOW	nitor and		Engineering Isolate the hazard.		
is the second m	rchy of Controls: ost effective metho nging the work is th	d of controlling a	hazard. Enginee	ring by isolati		et. 'ive, while	rd. Substitution Administrative effective		Administrative Change the work.  PPE		

				PERS		TIVE EQUIPM					
		Select the app	ropriate PPL	abo. ~uitab	ic or the equip	oment used or	the job task	being perform	ned (if applica	able).	
FOOT PROTECTION	HAND PROTECTION	HEAD PROTECTION	ARING STION	F' CTIO	RL PIRATORY PROTECTION	FACE PROTECTION	HIGH-VIS CLOTHING	PROTECTIVE CLOTHING	FALL PROTECTION	SUN PROTECTION	HAIR/JEWELLERY SECURED
Other PPE R	equired:										
	Pe	ermit or Licen	ses Requirem	ents		Mandatory Qualifications and Training					



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
Pre-start planning and consultation	Unidentified underground services     Unmarked overhead power lines     Inadequate worker competence     Conflicting work activities     Emergency response delays	4A	Obtain and review current Dial Before Yor or (DBYD) and network operator asset plans for all work areas before mobilisation  Contact the relevant electricity supply author. It confirm voltage, ownership, isolation requirements and any permit conditions for overhead and undergrifed assets.  Develop a task-specific SWi, and Job Safety Air visic or 1) that identifies High Risk Construction Work under WHS Resolution 2s and have it review or a competent supervisor.  Conduct a product in a product of the swift o	2M
Site establishment and traffic control	Unplanned vehicle movement Interaction with public traffic Restricted site access Poorly defined work area Slips trips and falls	ЗН	<ul> <li>Develop and implement a Traffic Management Plan (TMP) in accordance with local road authority requirements and AS 1742 for all works impacting roadways or footpaths</li> <li>Install advance warning signage, cone tapers, bollards, temporary barriers and delineation to separate work areas from live traffic and pedestrian routes</li> <li>Position work vehicles, EWPs and cranes so that they are outside minimum approach distances to overhead lines and do not require excessive slewing over public areas</li> <li>Erect secure exclusion zones around power poles, excavation areas, lifting zones and work at heights using barrier mesh or rigid barriers, and display no-entry signage</li> <li>Provide safe pedestrian detours with ramps, lighting and edge protection where footpaths are disrupted by pole works or street light installation</li> </ul>	2M



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
			Inspect ground surfaces for potholes, loose gravel and uneven pavement and level or plate over as required to provide stable access for workers and plant	
			Mark underground service locations on the group using paint and flags and keep plant, outriggers and augers away from identified services as per DP plans	
			• Instruct workers to maintain three points contact whe ccessing and exiting vehicles, EWPs and plant to reduce slip and fall incidents	
			• Implement spotters to guide reversing vehicle d plant and for sure no public or workers are within the vehicle blind spot or swing reads	
			• DO NOT allow public vehicles oedestrians to endesignated work exclusion zone under any circumstances	
			Verify that _emporary b _iers ai _signs ~spected at least daily and after any significant weather event or traffic _cident	
			Con Till e statul energised or de-energised), voltage level and ownership with the electricity supply author but re any rk is carried out on or near the asset	
			Arrang plan d outa s and isolation through the network operator for works that require deergisa in an obtain written access authority or permit to work	
			• Imp. he lock-out tag-out (LOTO) procedures at all isolation points, including locks, tags and ocume, on, and verify isolation before work begins	
	Contact with live co		• st all conductors and exposed parts using approved and in-date voltage detectors suited to the system voltage to confirm they are de-energised before touching	
Service identification	Unexpected equinent energisation		• Fit portable earths using approved equipment and procedures to discharge stored and induced energy, ensuring correct connection order (earth end first, then line end)	
and electrical isolation	Induced voltages     Arc flash	1A	Maintain minimum approach distances for live lines as specified by the network operator and WHS requirements; use insulated barriers or covers (tiger tails) where prescribed	2M
	Explosive failure of equiment		Assign a competent safety observer (spotter) to monitor separation distances between plant, tools and live electrical infrastructure when working near energised lines	
			• Prohibit the use of metallic tape measures, long-handled conductive tools or uninsulated ladders in close proximity to overhead lines	
			• Ensure switchboards, pillars and link boxes are inspected visually for damage, corrosion or signs of overheating before covers are removed	
			• DO NOT rely solely on network diagrams or verbal advice; always test for dead before starting work on conductors or terminations	
			• DO NOT bypass interlocks, protective devices or safety covers installed on electrical equipment	
	Falls from EWP			
Working at heights near overhead lines	Falls from ladder	4A		2M
	Contact with live conductors			



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	• Falling tools or materials • EWP tip-over	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
Plant and crane operation near lines	Plant contact with live conductors Uncontrolled slewing or boom movement Overloading of crane Utrigger failure Vehicle rollover	4A		2M



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
Excavation and pole foundation works	Underground service strike     Excavation collapse     Plant-person interaction     Falling into open excavations     Flying debris from auger	3H		2M



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
Power pole temporary support	Pole collapse Structural instab Snapping stay wire Falling conductors Struck by shifting suppo	JA.		2M
Power pole removal	Uncontrolled pole fall	4A		2M



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	• Falling conductors • Falling hardware • Crane overload • Flying debris from cutting	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
Power pole installation and energised transfer	Contact with live conductors Pole instability during placement Falling tools and fittings Dropped conductor Musculoskeletal strain	4A		2M



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
				1
	Electrical shock from socircuits     Falls from heights			
Installing and maintaining street lights	Contact with traffic     Dropped lanterns or brackets	3H		2M
	Glare affecting drivers			
				I



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
Cable terminations and connections	Electric shock     Arc flash during s     Incorrect phase connection     Short circuit from tools     Exposure to insulating compounds	ЗН		1L
Environmental and weather risk management	UV radiation exposure     Heat stress	3H		2M



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE  • High wind gusts  • Lightning strike  • Reduced visibility	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
Housekeeping and demobilisation	Residual live parts     Abandoned open excavations     Trip hazards from offcuts     Unsecured poles and materials     Public access to work area	ЗН		1L



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
				•

### hluesafe



#### **EMERGENCY RESPONSE - CALL 000 FOR EMERGENCIES**

Ensure to have an Emergency Management Plan in place as well as adequate numbers of trained first aid staff with easy access to fully stocked first aid kits, rescue equipment, material safety data sheets, adequate access to emergency communication equipment and fire-fighting equipment suitable for all classes of fire and ignition sources.

#### LEGISLATIVE REFERENCES

RELEVANT LEGISLATION AND CODES OF PRACTICE. DELETE THE LEGISLATIVE REFERENCES. ANY STATE AT ARE NOT APPLICABLE.

#### **Queensland & Australian Capital Territory**

Work Health and Safety Act 2011

Work Health and Safety Regulations 2011

Legislation QLD: https://www.worksafe.qld.gov.au/laws-and-compliance/work-health-and-safety-laws Codes of Practice QLD: https://www.worksafe.qld.gov.au/laws-and-compliance/codes-of-practice

Legislation ACT: https://www.worksafe.act.gov.au/laws-and-compliance/acts-and-regulations

Codes of Practice ACT: https://www.worksafe.act.gov.au/laws-and-compliance/codes-of-practice

#### **New South Wales**

Work Health and Safety Act 2011

Work Health and Safety Regulations 2025

Legislation NSW: https://www.safework.nsw.gov.au/legal-obligations/legislati

Codes of Practice NSW: https://www.safework.nsw.gov.au/resource-library/lis

#### **Northern Territory**

Work Health and Safety (National Uniform Legislation) Act 2011

Work Health and Safety (National Uniform Legislation) Regulation 201

Legislation NT: https://worksafe.nt.gov.au/laws-and-compliance/wo

Codes of Practice NT: https://worksafe.nt.gov.au/f -resourd

#### South Australia

Work Health and Safety Act 2012 (SA)

Work Health and Safety Regulations 2012 (SA)

Legislation for SA: https://www.safework.sa.gov.au/resources/le lation

Codes of Practice for SA: https://www.safework.sa.gov.au/wor/ aces/codes-of-practice#COPs

#### Tasmania

Work Health and Safety Act 2012

Work Health and Safety (Transitional and Consequential Provisions) Act 2012

Work Health and Safety Regulations 2012

Work Health and Safety (Transitional) Regulations 2012

Legislation for TAS: https://worksafe.tas.gov.au/topics/laws-and-compliance/acts-and-regulations

Codes of Practice for TAS: https://worksafe.tas.gov.au/topics/laws-and-compliance/codes-of-practice

Details of permits, licenses or access required by regulatory bodies (add or delete as required):

- Permits from local council
- Authorisation to commence work
- Any required documents.

#### Victoria

Or pational Health a. Safety Act J4

Occ ational Health and afety gulations 2017

Legis on VIC: https://www ksafe.vic.gov.au/occupational-health-and-safety-act-and-

tes of actice V/ attps://www.worksafe.vic.gov.au/compliance-codes-and-codes-practice

#### Western Australia

Work Health and Safety Act 2020

Work Health and Safety Regulations 2022

Legislation Western Australia: https://www.commerce.wa.gov.au/worksafe/legislation Codes of Practice WA: https://www.commerce.wa.gov.au/worksafe/codes-practice

#### Safe Work Australia Links

Law and Regulation (All States): https://www.safeworkaustralia.gov.au/law-and-regulation Model Codes of Practice: https://www.safeworkaustralia.gov.au/resources-publications/modelcodes-of-practice

#### Model Codes of Practice

- Managing noise and preventing hearing loss at work
- Confined spaces
- Labelling of workplace hazardous chemicals
- Managing risks of hazardous chemicals in the workplace
- Welding processes
- First aid in the workplace
- Managing the risk of falls at workplaces
- Hazardous manual tasks
- Managing the risk of falls in housing construction
- Managing electrical risks in the workplace
- Demolition work
- Excavation work
- Work health and safety consultation, cooperation and coordination
- Managing the work environment and facilities
- How to manage work health and safety risks
- Managing risks of plant in the workplace
- Construction work





#### SIGNATORIES OF THE SAFE WORK METHOD STATEMENT

The signed and dated personnel listed below have cooperated in the consultation and development of this Safe Work Method Statement which has been approved by the Person/s Conducting a Business or Undertaking (PCBU). In signing this Safe Work Method Statement each individual acknowledges and confirms that they have read this SWMS in full, having raised any questions for items on this Safe Work Method Statement that require clarification, and confirms that they are competent, skilled and knowledgeable for the task assigned to them. Every person acknowledges that they have received the relevant training and qualifications where required, before carrying out any work contained in this Safe Work Method Statement. By signing this Safe Work Method Statement each individual agrees to work safely, to follow any safe work instructions which are provided, and agrees to use all Personal Protective Equipment where appropriate.

Worker Name	Signature

### SAFE WORK NOTHER STATEMENT MONITORING AND REVIEW

The SWMS must be reviewed regularly to make sure it remains fective of must be reviewed (and revised if necessary) if relevant control measures are rovised. The view respectively should be carried out in consultation with workers (including contractors and other substitutions) and their health and safety representatives who represented that work group at the workplace.

When the SWMS has been revised the PCBU must ensure that advised that a revision has been made and how they can access the revised SWMS, including all persons who will need to change a work procedure or system as a rest of the review are advised of the changes in a way that will enable them to implement their duties and the revised SWMS. All workers that will be involved in the work must be provided with the relevant information and instruction that will assist them to understand and implement the revised SWMS.

The SWMS must be monitored regularly for the effectiveness of ensuring hazard controls are effective in reducing the risk of incidents, keeping the workplace safe for all personnel. The person responsible for monitoring the effectiveness of the Safe Work Method Statement should employ a multi-faceted approach which includes but is not limited to:

- Spot Checks.
- 2. Consultation with workers, contractors and sub-contractors.
- 3. Internal audits on a continual basis.

An approach of continuous improvement, promptly recording inconsistencies or deficiencies, followed up by immediate corrective action and consultation with all relevant personnel ensures that the PCBU is consistently developing ever-improving systems of safe work principles.

REVIEW NUMBER	1	2	3	4	5	6	7
NAME							
INITIALS							
DATE							

Version 2.5 Authorised by Review # Date of Issue: Review Date: 15





### SAFE WORK METHOD STATEMENT REVIEW CHECKLIST

This Safe Work Method Statement Review Checklist is to be followed and used upon initial development of the SWMS to help ensure that all steps have been adequately taken before work commences. Think of this document as an internal audit review checklist before commencing work, and may form part of a Toolbox Talk (safety meeting) and may be used as an opportunity for education and training.

ITEMS WHICH MUST BE INCLUDED IN THE SWMS	COMPLETED	COMMENTS
The company details have been entered, including the project name and address.		
All relevant personnel consulted during the development of the SWMS.		
Name, signature, position and date signed of the person approving the SWMS.		
Specific personnel and qualifications, experience is noted in the SWMS.	7	
Provides a step-by-step process of tasks required to carry out the activity or task.	k	
Adequate risk assessment of any identified hazards has been completed.	$\boxtimes$	
Foreseeable hazards are identified and documented for each step.	$\boxtimes$	
Any hazards listed in any site risk assessments have been added to the SWMS		
SWMS initial risk (IR) column as well as residual risk (RR) colum mpleted.	$\boxtimes$	
Check control measures added to the SWMS are the most effective selections.		
Responsible person is assigned and listed on the part of the important of	$\boxtimes$	
Permit or licenses requirements specified, sur as Hot Work, Electric Work, Work at Heights etc.	$\boxtimes$	
SWMS identifies plant and equipment to be use	$\boxtimes$	
Details of inspection checks required for any equipment listed an onthe SWMS.	$\boxtimes$	
Describes any mandatory qualifications, experience, use or skills required to perform the work.	$\boxtimes$	
Applicable personal protective equipment is selected on the SWMS.		
Reflects and documents any legislative references and/or Australian Standards.	$\boxtimes$	
Identifies any hazardous substances used with specific control measures in line with any SDS.	$\boxtimes$	
REVIEWED BY	DATE REV	/IEWED
SIGNATURE	DATE COM	PLETED