



Preventive Maintenance On Auto	omatic Doors   SAFE WOR	K METHOD STATEMENT (SV	VMS)
TASK OR ACTIV	ITY: Preventive Maintenance On	Automatic Doors	
Business Name:		ABN:	SWMS#
Business Address:			
Contact Person:	Phone:	E il:	
THIS SAFE WORK METHOD	STATEMENT IS APPROV TO BY	THE PCL OF THE ROJECT	
Under the Work Health and Safety Regulation (WHS Regulation), a person conduct the proposed work starts.	cting a business or undo	required to en that a safe work method	statement (SWMS) is prepared before
Full Name:			
Signature:	NY	Title:	Date:
Details of the person(s) responsible for ensuring implementation, monitoring a	apliance the VMS a well as review	s and modifications of the SWMS.	
Full Name:		Title:	Phone:
ALL PERSONNEL PARTICIPATING IN ANY ACTIVITY ON THIS SIMS MANY HAVE THE FOLLOWING COMMUNICATED	NA. 2 OF ALL RELEVANT PERSONN EVELOPMENT AND APPROVAL OF	EL WHO HAVE BEEN CONSULTED AND C THIS SWMS	OMMUNICATED TO IN THE
Safety meetings or toolbox talks will be sched and in account with gislative requirements to first identify any site hazards, comparing those hazards and then to further take steps to either eliminate or continuous each hazard.			
If an incident or a near miss occurs, all work must ste, an atately. Depending on the severity of the incident, a meeting will be called with all workers to amend the SWMS if required. The meeting may also be an educational opportunity.			
Any changes made to the SWMS after an incident or a near miss must be approved by the Person Conducting Business or Undertaking and communicated to all relevant personnel.			
The SWMS must be kept and be available for inspection at least until the work is completed. Where a SWMS is revised, all versions should be kept. If a notifiable incident occurs in relation to which the SWMS relates, then the SWMS must be kept for at least two years from the occurrence of the notifiable incident.			

Version 2.5 Authorised by Review # Date of Issue: Review Date: 1





CLIENT OR PRINCIPAL	CONTRACTOR DETAILS
Client:	SCOPE OF WORKS
Project Name:	
Project Address:	
Project Manager:	
Contact Phone:	
Date SWMS supplied to Project Manager:	
ANY HIGH BIOK CONSTRUCTOR	NAME OF THE POLIT
ANY HIGH-RISK CONSTRUCTOR	N WC & BEIN C ARIED OUT
☐ involves a risk of a person falling more than 2 meters	is carried out on or near pressurised gas mains or piping
☐ is carried out on a telecommunication tower	carried out on or near chemical, fuel or refrigerant lines
☐ involves demolition of an element of a structure that is load-bearing	$\square$ is carried out on or near energised electrical installations or services
☐ involves demolition of an element related to the physical integral of a functure	☐ is carried out in an area that may have a contaminated or flammable atmosphere
☐ involves, or is likely to involve, disturbing asb	☐ involves tilt-up or precast concrete
☐ involves structural alteration or repair that —quires term — v sup —rt to prevent collapse	☐ is carried out on, in or adjacent to a road, railway, shipping lane or other traffic corridor
☐ is carried out in or near a confined space	☐ is carried out in an area of a workplace where there is any movement of powered mobile plant
☐ is carried out in/near a shaft or trench deeper that. tunnel involving use of explosives	☐ is carried out in areas with artificial extremes of temperature.
$\square$ is carried out in or near water or other liquid that involves a risk of drowning.	☐ involves diving work.
ANY HIGH-RISK MACHINER	Y OR EQUIPMENT NEARBY

Version 2.5 Authorised by Review # Date of Issue: Review Date: 2



RISK MATRIX									
LIKELIHOOD	INSIGNIFICANT	MINOR	MODERATE	MAJOR	CATASTROPHIC	SCORE	ACTION	HEIRARCHY OF CONTROLS	
ALMOST CERTAIN	3 HIGH	3 HIGH	4 ACUTE	4 ACUTE	4 ACUTE	SCORE	ACTION	Elimination Remove the hazard.	
LIKELY	2 MODERATE	3 HIGH	3 HIGH	4 ACUTE	4 ACUTE	4A ACUTE	DO NOT PROCE	Substitution	
POSSIBLE	1 LOW	2 MODERATE	3 HIGH	4 ACUTE	4 ACUTE	3H HIGH	Review before work starts.	Replace the hazard.	
UNLIKELY	1 LOW	1 LOW	2 MODERATE	3 HIGH	4 ACUTE	2M MODERATE	Ensure control measures in place.	Isolate People from the hazard	
RARE	1 LOW	1 LOW	2 MODERATE	3 HIGH	3 HIGH	1L LOW	nitor and	Engineering Isolate the hazard.	
is the second m	Administrative  Change the work.  Change the work is the fourth most effective method. PPE (Personal Protective Equipment), the least effective								

				PERS		TIVE EQUIPM					
		Select the app	propriate PPL	abo√ ≃uitab	ic or the equi	pment used or	the job task	being perforr	ned (if applica	ıble).	
FOOT PROTECTION	HAND PROTECTION	HEAD PROTECTION	HEARING ETION	P ECTION	R PIRATORY PROTECTION	FACE PROTECTION	HIGH-VIS CLOTHING	PROTECTIVE CLOTHING	FALL PROTECTION	SUN PROTECTION	HAIR/JEWELLERY SECURED
Other PPE R	Required:										
	Pe	ermit or Licen	ses Requirem	ents			Ma	andatory Qual	ifications and	Training	



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
1. Preparation	Tripping over tools, Incorrect use of tools, Electrical hazards	3H	<ul> <li>Ensure all tools are stored in designated a cust when not in use to prevent trip hazards.</li> <li>Conduct a toolbox talk prior to commencing bork to curvess proper tool usage and storage.</li> <li>Use insulated tools designed for electrical work aminimise the risk of electric shock.</li> <li>Confirm that the power supposite disconnected betwee beginning any maintenance procedures.</li> <li>Equip workers with a small projective equipment, so as non-slip shoes, to avoid tripping incidents.</li> <li>Clearly markes work are with smaller or bases to alert others of potential hazards.</li> <li>Provide train or for employees on the project operation and handling of maintenance tools and equipment.</li> <li>Regular inspections for wear and tear, replacing them as necessary to ensure safe operation.</li> <li>Use protate alighting a low-light conditions to increase visibility and reduce the chance of missteps.</li> <li>Implement a necessary to ensure machinery remains off while maintenance is being priorme.</li> <li>Mainus clear workspace by removing debris and ensuring adequate walking space around the area.</li> <li>Insure qualified personnel conduct an electrical hazard assessment before undertaking any work.</li> </ul>	2M
2. Inspecting the door	Electric shock, Dropping heavy components causing foot injury	ЗН	<ul> <li>Conduct a site-specific risk assessment prior to starting the inspection to identify any potential hazards.</li> <li>Ensure all personnel are trained and competent in handling electrical components and tools.</li> <li>De-energise the automatic door system by disconnecting the power supply before commencing inspection.</li> <li>Use insulated tools and wear electrically resistant gloves when working near electrical components.</li> <li>Implement lockout/tagout procedures to prevent accidental re-energisation during maintenance.</li> <li>Wear appropriate personal protective equipment (PPE), including safety boots with steel toe caps, to mitigate foot injury risks.</li> <li>Use lifting aids or additional personnel when required to prevent manual handling injuries from heavy components.</li> <li>Maintain a clear work area around the door to reduce tripping hazards and facilitate movement.</li> <li>Inspect and secure moving parts to prevent inadvertent operation during inspection.</li> <li>Regularly communicate with team members using a two-way radio or another reliable communication device to ensure awareness of ongoing activities.</li> <li>Clearly mark and isolate the work area with barricades and signage to restrict unauthorised access.</li> <li>Identify and replace any damaged or worn-out component to prevent malfunction-related risks.</li> </ul>	2M



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
			- Ensure adequate lighting in the inspection area to enhance visibility and accuracy.	
			- Keep emergency contact numbers and first aid kits readily accessible in case of an incident.	
3. Turning off the door's power supply	Electrical hazards, Tripping Over Tools	3H	<ul> <li>Ensure only trained and authorised person to perform the task of turning off the power supply.</li> <li>Clearly label and isolate the electrical circle associate with the automatic doors before commencing work.</li> <li>Use insulated tools and were appropriate person throtective collipment (PPE), such as rubber gloves, when handling electrical completents.</li> <li>Display warning sit to blicating paintenance work to being carried out to alert others in the vicinity.</li> <li>Conduct a ricroassessment specific to the task or disabling the power supply for automatic doors.</li> <li>Verify with a suitage test or that the proceeding indeed switched off before proceeding with any further paintenance as a suites.</li> <li>Keep the tork are clear of unnecessary tools and materials to reduce tripping hazards.</li> <li>Arrant annecure bles and extension leads to prevent tripping and ensure they do not obstruct pathway.</li> <li>In intain good to be keeping practices, ensuring tools are returned to their designated places immediate after use.</li> <li>Istablish an exclusion zone around the work area to prevent unauthorised access and potential at telents.</li> <li>Use barrier tapes or physical barriers to demarcate the work area and enhance visibility.</li> <li>Communicate clearly with team members about the ongoing task and potential hazards involved.</li> <li>Prioritise emergency procedures to address any incidents, including having a spotter or colleague present during the operation.</li> </ul>	2M
4. Removing the door's cover	Sharp objects could cause cuts, Falling objects	2M		1L



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
Checking circuits and wiring	Electrical shocks, Fire due to amp	4A		2M
wiring	overload	4A		ZIVI



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
6. Cleaning and maintaining motor box	Chemical exposure from cleaners, Slippery surface from spillage			1L
7. Replacing any damaged parts	Incorrect parts used causing malfunctioning, Hand pinched or caught between parts	4A		2M



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
8. Checking safety devices	Failure of equipment can lead to an accident	ЗН		1L



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
9. Checking the door operation	Malfunction causing serious injury	ЗН		1L



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
10. Cleaning the door and surrounding area	Slippery surfaces due to water, Chemical exposure with cleaning fluid	ЗН		1L
11. Lubricating movable parts	Leaking lubricant causing slippery floor, Entrapment of fingers	ЗН		2M



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
				•
12. Testing door operations again	Electric shock, Mannotion causing injury	ЗН		1L
13. Putting the cover back on	Trapped fingers, sharp edge cuts	2M		1L



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
14. Turning the power back on	Electrical shock, Trips due to cluttered work area	ЗН		1L



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
15. Completing the paperwork	Safety information omitted, Paper cut	1L		1L
16. Cleaning and putting away tools	Tripping over tools, Incorrect storage of tools causing accidents	2M		1L



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
17. Final check with client	Inadequate training of client causing accident	2M		1L



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
18. Departure from site	Trips due to cluttered work area	2M		1L



#### **EMERGENCY RESPONSE - CALL 000 FOR EMERGENCIES**

Ensure to have an Emergency Management Plan in place as well as adequate numbers of trained first aid staff with easy access to fully stocked first aid kits, rescue equipment, material safety data sheets, adequate access to emergency communication equipment and fire-fighting equipment suitable for all classes of fire and ignition sources.

#### LEGISLATIVE REFERENCES

RELEVANT LEGISLATION AND CODES OF PRACTICE. DELETE THE LEGISLATIVE REFERENCES. ANY STATE OF AT ARE NOT APPLICABLE.

#### **Queensland & Australian Capital Territory**

Work Health and Safety Act 2011

Work Health and Safety Regulations 2011

 $\textbf{Legislation QLD:} \ \underline{\textbf{https://www.worksafe.qld.gov.au/laws-and-compliance/work-health-and-safety-laws}$ 

Codes of Practice QLD: https://www.worksafe.qld.gov.au/laws-and-compliance/codes-of-practice Legislation ACT: https://www.worksafe.act.gov.au/laws-and-compliance/acts-and-regulations

Codes of Practice ACT: https://www.worksafe.act.gov.au/laws-and-compliance/codes-of-practice

#### **New South Wales**

Work Health and Safety Act 2011

Work Health and Safety Regulations 2017

Legislation NSW: https://www.safework.nsw.gov.au/legal-obligations/legislati

Codes of Practice NSW: https://www.safework.nsw.gov.au/resource-library/lis > odes-oi racti

#### **Northern Territory**

Work Health and Safety (National Uniform Legislation) Act 2011

Work Health and Safety (National Uniform Legislation) Regulation 201

Legislation NT: https://worksafe.nt.gov.au/laws-and-compliance/wo\_place-

Codes of Practice NT: https://worksafe.nt.gov.au/f

#### South Australia

Work Health and Safety Act 2012 (SA)

Work Health and Safety Regulations 2012 (SA)

Legislation for SA: https://www.safework.sa.gov.au/resources/le\_lation

Codes of Practice for SA: <a href="https://www.safework.sa.gov.au/wor">https://www.safework.sa.gov.au/wor</a> aces/codes-of-practice#COPs

#### Tasmania

Work Health and Safety Act 2012

Work Health and Safety (Transitional and Consequential Provisions) Act 2012

Work Health and Safety Regulations 2012

Work Health and Safety (Transitional) Regulations 2012

Legislation for TAS: https://worksafe.tas.gov.au/topics/laws-and-compliance/acts-and-regulations

Codes of Practice for TAS: https://worksafe.tas.gov.au/topics/laws-and-compliance/codes-of-practice

Details of permits, licenses or access required by regulatory bodies (add or delete as required):

- Permits from local council
- Authorisation to commence work
- Any required documents.

#### Victoria

Occupational Health al. Safety Act

Occupational Health and affety gulations 2017

Legis on VIC: https://www.wksafe.vic.gov.au/occupational-health-and-safety-act-and-

gulat

des on actice VI autros://www.worksafe.vic.gov.au/compliance-codes-and-codes-practice

#### Western Australia

Work Health and Safety Act 2020

Work Health and Safety Regulations 2022

Legislation Western Australia: <a href="https://www.commerce.wa.gov.au/worksafe/legislation">https://www.commerce.wa.gov.au/worksafe/legislation</a> Codes of Practice WA: <a href="https://www.commerce.wa.gov.au/worksafe/codes-practice">https://www.commerce.wa.gov.au/worksafe/codes-practice</a>

#### Safe Work Australia Links

Law and Regulation (All States): <a href="https://www.safeworkaustralia.gov.au/law-and-regulation">https://www.safeworkaustralia.gov.au/law-and-regulation</a> Model Codes of Practice: <a href="https://www.safeworkaustralia.gov.au/resources-publications/model-codes-of-practice">https://www.safeworkaustralia.gov.au/resources-publications/model-codes-of-practice</a>

#### **Model Codes of Practice**

- Managing noise and preventing hearing loss at work
- Confined spaces
- Labelling of workplace hazardous chemicals
- Managing risks of hazardous chemicals in the workplace
- Welding processes
- First aid in the workplace
- Managing the risk of falls at workplaces
- Hazardous manual tasks
- Managing the risk of falls in housing construction
- Managing electrical risks in the workplace
- Demolition work
- Excavation work
- Work health and safety consultation, cooperation and coordination
- Managing the work environment and facilities
- How to manage work health and safety risks
- Managing risks of plant in the workplace
- Construction work





#### SIGNATORIES OF THE SAFE WORK METHOD STATEMENT

The signed and dated personnel listed below have cooperated in the consultation and development of this Safe Work Method Statement which has been approved by the Person/s Conducting a Business or Undertaking (PCBU). In signing this Safe Work Method Statement each individual acknowledges and confirms that they have read this SWMS in full, having raised any questions for items on this Safe Work Method Statement that require clarification, and confirms that they are competent, skilled and knowledgeable for the task assigned to them. Every person acknowledges that they have received the relevant training and qualifications where required, before carrying out any work contained in this Safe Work Method Statement. By signing this Safe Work Method Statement each individual agrees to work safely, to follow any safe work instructions which are provided, and agrees to use all Personal Protective Equipment where appropriate.

Worker Name	Signature	Date

#### SAFE WORK IN THE STATEMENT MONITORING AND REVIEW

The SWMS must be reviewed regularly to make sure it remains a fective of must be reviewed (and revised if necessary) if relevant control measures are revised. The view process should be carried out in consultation with workers (including contractors of the SWMS and their health and safety representatives who represented that work group at the workplace.

When the SWMS has been revised the PCBU mast ensure that advised that a revision has been made and how they can access the revised SWMS, including all persons who will need to change a work procedure or system as a rest of the review are advised of the changes in a way that will enable them to implement their duties and the involved in the work must be provided with the relevant information and instruction that will assist them to understand and implement the revised SWMS.

The SWMS must be monitored regularly for the effectiveness of ensuring hazard controls are effective in reducing the risk of incidents, keeping the workplace safe for all personnel. The person responsible for monitoring the effectiveness of the Safe Work Method Statement should employ a multi-faceted approach which includes but is not limited to:

- Spot Checks.
- 2. Consultation with workers, contractors and sub-contractors.
- 3. Internal audits on a continual basis.

An approach of continuous improvement, promptly recording inconsistencies or deficiencies, followed up by immediate corrective action and consultation with all relevant personnel ensures that the PCBU is consistently developing ever-improving systems of safe work principles.

REVIEW NUMBER	1	2	3	4	5	6	7
NAME							
INITIALS							
DATE							

Version 2.5 Authorised by Review # Date of Issue: Review Date: 17





### SAFE WORK METHOD STATEMENT REVIEW CHECKLIST

This Safe Work Method Statement Review Checklist is to be followed and used upon initial development of the SWMS to help ensure that all steps have been adequately taken before work commences. Think of this document as an internal audit review checklist before commencing work, and may form part of a Toolbox Talk (safety meeting) and may be used as an opportunity for education and training.

ITEMS WHICH MUST BE INCLUDED IN THE SWMS	COMPLETED	COMMENTS
The company details have been entered, including the project name and address.		
All relevant personnel consulted during the development of the SWMS.		
Name, signature, position and date signed of the person approving the SWMS.		
Specific personnel and qualifications, experience is noted in the SWMS.	7	
Provides a step-by-step process of tasks required to carry out the activity or task.		
Adequate risk assessment of any identified hazards has been completed.		
Foreseeable hazards are identified and documented for each step.		
Any hazards listed in any site risk assessments have been added to the SWMS		
SWMS initial risk (IR) column as well as residual risk (RR) column pupleted.		
Check control measures added to the SWMS are the most effective selective selective.		
Responsible person is assigned and listed on the part the important of measures.		
Permit or licenses requirements specified, sur as Hot Work, Electric Work, Work at Heights etc.		
SWMS identifies plant and equipment to be us		
Details of inspection checks required for any equipment listed an inoted on the SWMS.		
Describes any mandatory qualifications, experience, and or skills required to perform the work.		
Applicable personal protective equipment is selected on the SWMS.		
Reflects and documents any legislative references and/or Australian Standards.		
Identifies any hazardous substances used with specific control measures in line with any SDS.		
REVIEWED BY	DATE REVIE	WED
SIGNATURE	DATE COMPL	ETED