

Switch High Voltage	SAFE WORK METHOD S	STATEMENT (SWMS)	
TAS	K OR ACTIVITY: Switch High Vo	ltage	
Business Name:		ABN:	SWMS#
Business Address:			
Contact Person:	Phone:	E ail:	
THIS SAFE WORK METHOD	STATEMENT IS APPROVED BY	THE PC OF TP' ROJECT	
THIS SAFE WORK METHOD	STATEMENT IS APPROX 9 BT	THE PCT OF IP . ROJECT	
Under the Work Health and Safety Regulation (WHS Regulation), a person conductive proposed work starts.	cting a business or und ing (P V) is	required to el ethat a safe work method	statement (SWMS) is prepared before
Full Name:			
Signature:	NY	Title:	Date:
Details of the person(s) responsible for ensuring implementation, monitoring	compliant e of the SWIL as well as re	eviews and modifications of the SWMS.	
Full Name:		Title:	Phone:
ALL PERSONNEL PARTICIPATING IN ANY ACTIVITY ON THIS VMS HAVE THE FOLLOWING COMMUNICATED	NA. 2 OF ALL RELEVANT PERSONN EVELOPMENT AND APPROVAL OF	IEL WHO HAVE BEEN CONSULTED AND THIS SWMS	COMMUNICATED TO IN THE
Safety meetings or toolbox talks will be sched ed in according e with regislative requirements to first identify any site hazards, to continue the those hazards and then to further take steps to either eliminate or con			
If an incident or a near miss occurs, all work must standardly. Depending on the severity of the incident, a meeting will be called with all workers to amend the SWMS if required. The meeting may also be an educational opportunity.			
Any changes made to the SWMS after an incident or a near miss must be approved by the Person Conducting Business or Undertaking and communicated to all relevant personnel.			
The SWMS must be kept and be available for inspection at least until the work is completed. Where a SWMS is revised, all versions should be kept. If a notifiable incident occurs in relation to which the SWMS relates, then the SWMS must be kept for at least two years from the occurrence of the notifiable incident.			

Version 2.5 Authorised by Review # Date of Issue: Review Date: 1



CLIENT OR PRINCIPAL	CONTRACTOR DETAILS
Client:	SCOPE OF WORKS
Project Name:	
Project Address:	
Project Manager:	
Contact Phone:	
Date SWMS supplied to Project Manager:	
ANY HIGH-RISK CONSTRUCTOR	ON WC & BEIN C & RIED OUT
involves a risk of a person falling more than 2 meters	is carried out on or near pressurised gas mains or piping
☐ is carried out on a telecommunication tower	carried out on or near chemical, fuel or refrigerant lines
☐ involves demolition of an element of a structure that is load-hearing	☐ is carried out on or near energised electrical installations or services
☐ involves demolition of an element related to the physical interrity structure	☐ is carried out in an area that may have a contaminated or flammable atmosphere
☐ involves, or is likely to involve, disturbing as	☐ involves tilt-up or precast concrete
involves structural alteration or repair the requires to rary so port to prevent collapse	☐ is carried out on, in or adjacent to a road, railway, shipping lane or other traffic corridor
☐ is carried out in or near a confined space	☐ is carried out in an area of a workplace where there is any movement of powered mobile plant
is carried out in/near a shaft or trench deeper an or tunnel involving use of explosives	☐ is carried out in areas with artificial extremes of temperature.
is carried out in or near water or other liquid that involves a risk of drowning.	involves diving work.
ANY HIGH-RISK MACHINER	Y OR EQUIPMENT NEARBY

Version 2.5 Authorised by Review # Date of Issue: Review Date: 2



RISK MATRIX											
LIKELIHOOD	INSIGNIFICANT	MINOR	MODERATE	MAJOR	CATASTROPHIC	SCORE	ACTION		HEIRARCHY OF CONTROLS		
ALMOST CERTAIN	3 HIGH	3 HIGH	4 ACUTE	4 ACUTE	4 ACUTE	SCORE	SCORE	SCORE	ACTION		Elimination Remoy e the hazard.
LIKELY	2 MODERATE	3 HIGH	3 HIGH	4 ACUTE	4 ACUTE	4A ACUTE	DO NOT PROCE		Substitution		
POSSIBLE	1 LOW	2 MODERATE	3 HIGH	4 ACUTE	4 ACUTE	3H HIGH	Review before work starts.		Replace the hazard.		
UNLIKELY	1 LOW	1 LOW	2 MODERATE	3 HIGH	4 ACUTE	2M MODERATE	Ensure control measures in place.		Isolation Isolate People from the hazard		
RARE	1 LOW	1 LOW	2 MODERATE	3 HIGH	3 HIGH	1L LOW	nitor and records		Engineering Isolate the hazard.		
is the second m	archy of Controls: nost effective methologing the work is	od of controlling a	a hazard. Engine	ering by isolat	ion is the nost of	e. tive, while	ard. Substitution e Administrative least effective		Administrative Change the work.		

						TIVE EQUIPM					
		Select the app	propriate PPL	abo suitak	ok for the equip	oment used or	the job task	being perfori	med (if applica	able).	
FOOT PROTECTION	HAND PROTECTION	HEAD PROTECTION	THE ARING STION	P _cCTION	PROTECTION	FACE PROTECTION	HIGH-VIS CLOTHING	PROTECTIVE CLOTHING	FALL PROTECTION	SUN PROTECTION	HAIR/JEWELLERY SECURED
Other PPE R	equired:										
	Pe	ermit or Licen	ses Requirem	ients		Mandatory Qualifications and Training					



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
1. Preparation	Incorrect documentation, poor communication	3H	- Ensure all required documentation is reviewed and approved by authorised personnel before commencing work. - Verify that all personnel involved have the near my qualifications and training for high voltage work. - Conduct a thorough site-sucific risk assessment to identify and address potential hazards. - Use clear, concise, and standardised language in the ocumentation to avoid misunderstandings. - Hold pre-work to angs on hall norm members to ensure everyone understands their roles and responsibilities. - Implement a communication plan the condess regular updates and designated communication chart. - Continuent all confact information for emergency contacts and stakeholders is up to date. - Establin a main on mmand to ensure clear authority during operations. - Provide hard notices or digital access to all relevant documentation on site for easy reference by the teas. - Clearly usel and organise documents to prevent confusion or loss of critical information. - Nijze checklists to verify all preparation steps are completed accurately. - Assign a dedicated team member to oversee and coordinate communication efforts during the preparation phase. - Ensure that any changes in protocol or information are communicated promptly to all affected parties. - Regularly review and update documentation to reflect current best practices and regulatory requirements.	2M
2. Site Inspection	Uneven surfaces, electrical faults	4A	 Conduct a thorough walk-through of the site to identify uneven surfaces and ensure pathways are clearly marked. Use signage and barriers to alert workers to areas with uneven surfaces or potential electrical hazards. Ensure all personnel wear appropriate personal protective equipment (PPE), including insulated gloves and footwear designed for electrical work. Employ mechanical aids or lifting gear to move heavy equipment, reducing the risk of trips and falls on uneven ground. Implement regular maintenance checks of equipment to ensure they are in good working condition, minimising the risk of electrical faults. Assign a trained and competent supervisor to oversee activities and ensure compliance with safety protocols. 	ЗН



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS - Conduct toolbox talks to educate workers on recognising and addressing risks associated with uneven surfaces and electrical faults. - Ensure all electrical installations and repairs are surfied out by licensed and qualified electricians. - Introduce a permit-to-work system for high surage tasks to outline specific safety requirements and authorisations required before commencing work. - Develop an emergency response plan, converted and details for first aid, firefighting, and evacuation procedures in case of an electrical incident.	RESIDUAL RISK
3. Isolation Procedure	Inadequate isolation, incorrect tagging	ЗН	 Conduct a pre-job bringing with all personnel to review be isolation procedure and associated hazards. Ensure all employees into yed an trained and competent in high voltage isolation procedures. Use lockout agout (LOT) device an actuergy sources to prevent accidental energising. Verion at the agree solation pointswave been identified and marked on operational drawings. Use agree to courty indicate that equipment is isolated and under maintenance. Assign a devicated of fety observer to monitor compliance with isolation procedures. Confirm the-energisation using appropriate testing equipment before commencing work. Double-neck that all switches and disconnections align with the isolation plan. Pocume and log each step of the isolation process for accountability and traceability. Inclement a communication protocol to ensure all team members are aware of the current isolation status. Regularly audit the effectiveness of isolation tags and locks during the maintenance period. Have an approved supervisor inspect and sign off on the isolation setup prior to work commencement. Provide secondary containment or shielding around exposed conductors where applicable. Place redundant grounding measures in areas adjacent to isolated sections to safeguard against any residual electricity. 	2M
4. PPE Check	PPE failure, inadequate PPE	3Н		2M



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
5. Equipment Setup	Equipment malfunction, tripping hazards	4A]] ЗН



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
6. Verification	False readings, equipment miscalibration	3H		2M
7. High Voltage Switching	Arc flash, electric shock	4A		3H



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
8. Load Adjustment	Overloading circula, thermal of the	4A		3H
9. Safety Monitoring	Inattention, inadequate monitoring	3H		2M



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
10. Communication	Miscommunication, radio interference	ЗН		2M



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
				•
	7			
11. Environmental	Weather changes, lighting condition	ЗН		2M
Check				_



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
12. Emergency Protocols	Delayed response, ineffective procedures	4A		3H
13. Testing	Equipment damage, false security	ЗН		2M



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
				-
	G			
14. Documentation	Incomplete records, data loss	3Н		2M
				_
				•



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
15. Debriefing	Oversights in review, inaccurate reporting	ЗН		2M
16. Restoring Systems	Unintended reactivation, system instability	ЗН		2M



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
17. Waste Management	Incorrect disposal, chemical hazard	ЗН		1 2M



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
18. Equipment Maintenance	Lack of routine checks, wear and tear	ЗН		2M
19. Training	Insufficient training, knowledge gaps	3H		2M



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
				[
				I
				I
20. Final Review	Missed issues, inadequate conclusions	3H		2M
	, , , , , , , , , , , , , , , , , , ,			



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	RESIDUAL RISK
21. Reporting	Inaccurate data, In-compliance	ЗН		2M
				•



JOB STEP	POTENTIAL HAZARDS	IR	CONTROL MEASURES	RR
SPECIFIC WORK STEPS	HAZARDS THAT MAY ARISE	INITIAL RISK	SPECIFIC MEASURES TO BE PUT IN PLACE TO ELIMINATE OR CONTROL THE RISKS	





EMERGENCY RESPONSE - CALL 000 FOR EMERGENCIES

Ensure to have an Emergency Management Plan in place as well as adequate numbers of trained first aid staff with easy access to fully stocked first aid kits, rescue equipment, material safety data sheets, adequate access to emergency communication equipment and fire-fighting equipment suitable for all classes of fire and ignition sources.

LEGISLATIVE REFERENCES

RELEVANT LEGISLATION AND CODES OF PRACTICE. DELETE THE LEGISLATIVE REFERENCE. IN ANY STAFF THAT ARE NOT APPLICABLE

Queensland & Australian Capital Territory

Work Health and Safety Act 2011

Work Health and Safety Regulations 2011

Legislation QLD: https://www.worksafe.qld.gov.au/laws-and-compliance/work-health-and-safety-laws Codes of Practice QLD: https://www.worksafe.qld.gov.au/laws-and-compliance/codes-of-practice

Legislation ACT: https://www.worksafe.act.gov.au/laws-and-compliance/acts-and-regulations
Codes of Practice ACT: https://www.worksafe.act.gov.au/laws-and-compliance/codes-of-practice

New South Wales

Work Health and Safety Act 2011

Work Health and Safety Regulations 2017

Legislation NSW: https://www.safework.nsw.gov.au/legal-obligations/legis

Codes of Practice NSW: https://www.safework.nsw.gov.au/resource-library.

Northern Territory

Work Health and Safety (National Uniform Legislation) Act 201

Work Health and Safety (National Uniform Legislation) Regulations 26

Legislation NT: https://worksafe.nt.gov.au/laws-and-compliance/prkplate fety-lay

Codes of Practice NT: https://worksafe.nt.gov.av and-reso per des ractice

South Australia

Work Health and Safety Act 2012 (SA)

Work Health and Safety Regulations 2012 (S

Legislation for SA: https://www.safework.sa.gov.au/resources gislation

Codes of Practice for SA: https://www.safework.sa.gov.au/w/wplaces/codes-of-practice#COPs

Tasmania

Work Health and Safety Act 2012

Work Health and Safety (Transitional and Consequential Provisions) Act 2012

Work Health and Safety Regulations 2012

Work Health and Safety (Transitional) Regulations 2012

Legislation for TAS: https://worksafe.tas.gov.au/topics/laws-and-compliance/acts-and-regulations

Codes of Practice for TAS: https://worksafe.tas.gov.au/topics/laws-and-compliance/codes-of-practice

Details of permits, licenses or access required by regulatory bodies (add or delete as required):

- Permits from local council
- Authorisation to commence work
- Any required documents.

Victoria

Ocupational Health Safety A 2004

Oct ational Health an Safe* regulations 2017

- Legis ion VIC: https://www.orksafe.vic.gov.au/occupational-health-and-safety-act-and
 - ula. s
 - des of actice VI attps://www.worksafe.vic.gov.au/compliance-codes-and-codes-practice

Western Australia

Work Health and Safety Act 2020

Work Health and Safety Regulations 2022

Legislation Western Australia: https://www.commerce.wa.gov.au/worksafe/legislation

Codes of Practice WA: https://www.commerce.wa.gov.au/worksafe/codes-practice

Safe Work Australia Links

Law and Regulation (All States): https://www.safeworkaustralia.gov.au/law-and-regulation Model Codes of Practice: https://www.safeworkaustralia.gov.au/resources-publications/model-codes-of-practice

Model Codes of Practice

- Managing noise and preventing hearing loss at work
- Confined spaces
- Labelling of workplace hazardous chemicals
- Managing risks of hazardous chemicals in the workplace
- Welding processes
- First aid in the workplace
- Managing the risk of falls at workplaces
- Hazardous manual tasks
- Managing the risk of falls in housing construction
- Managing electrical risks in the workplace
- Demolition work
- Excavation work
- Work health and safety consultation, cooperation and coordination
- Managing the work environment and facilities
- How to manage work health and safety risks
- Managing risks of plant in the workplace
- Construction work



SIGNATORIES OF THE SAFE WORK METHOD STATEMENT

The signed and dated personnel listed below have cooperated in the consultation and development of this Safe Work Method Statement which has been approved by the Person/s Conducting a Business or Undertaking (PCBU). In signing this Safe Work Method Statement each individual acknowledges and confirms that they have read this SWMS in full, having raised any questions for items on this Safe Work Method Statement that require clarification, and confirms that they are competent, skilled and knowledgeable for the task assigned to them. Every person acknowledges that they have received the relevant training and qualifications where required, before carrying out any work contained in this Safe Work Method Statement. By signing this Safe Work Method Statement each individual agrees to work safely, to follow any safe work instructions which are provided, and agrees to use all Personal Protective Equipment where appropriate.

Worker Name	Signature	Date

SAFE WORK IN 'THIS 'S' ITEM ON MONITORING AND REVIEW

The SWMS must be reviewed regularly to make sure it remain effect, and must be reviewed (and revised if necessary) if relevant control measures are revised. The view as should be carried out in consultation with workers (including contractors as unputractors of the SWMS and their health and safety registeratives who represented that work group at the workplace.

When the SWMS has been revised the PCBD mest ensure the all persons involved with the work are advised that a revision has been made and how they can accept the revised SWMS, including all persons who will need to change a work procedure or system as a rest of the review are advised of the changes in a way that will enable them to implement their duties the total with the revised SWMS. All workers that will be involved in the work must be provided with the relevant information and instruction that will assist them to understand and implement the revised SWMS.

The SWMS must be monitored regularly for the effectiveness of ensuring hazard controls are effective in reducing the risk of incidents, keeping the workplace safe for all personnel. The person responsible for monitoring the effectiveness of the Safe Work Method Statement should employ a multi-faceted approach which includes but is not limited to:

- Spot Checks.
- Consultation with workers, contractors and sub-contractors.
- 3. Internal audits on a continual basis

An approach of continuous improvement, promptly recording inconsistencies or deficiencies, followed up by immediate corrective action and consultation with all relevant personnel ensures that the PCBU is consistently developing ever-improving systems of safe work principles.

REVIEW NUMBER	1	2	3	4	5	6	7
NAME							
INITIALS							
DATE							

Version 2.5 Authorised by Review # Date of Issue: Review Date: 20



SAFE WORK METHOD STATEMENT REVIEW CHECKLIST

This Safe Work Method Statement Review Checklist is to be followed and used upon initial development of the SWMS to help ensure that all steps have been adequately taken before work commences. Think of this document as an internal audit review checklist before commencing work, and may form part of a Toolbox Talk (safety meeting) and may be used as an opportunity for education and training.

ITEMS WHICH MUST BE INCLUDED IN THE SWMS	COMPLETED	COMMENTS
The company details have been entered, including the project name and address.		
All relevant personnel consulted during the development of the SWMS.		
Name, signature, position and date signed of the person approving the SWMS.		
Specific personnel and qualifications, experience is noted in the SWMS.		
Provides a step-by-step process of tasks required to carry out the activity or task.		
Adequate risk assessment of any identified hazards has been completed.	\boxtimes	
Foreseeable hazards are identified and documented for each step.		
Any hazards listed in any site risk assessments have been added to the SW. S.		
SWMS initial risk (IR) column as well as residual risk (RR) column completed.		
Check control measures added to the SWMS are the most effective secutions.		
Responsible person is assigned and listed on the placental of control measures.		
Permit or licenses requirements specified, so in as Hot Work, Electrical Work, Work at Heights etc.		
SWMS identifies plant and equipment to be		
Details of inspection checks required for any equipment lister are noted on the SWMS.		
Describes any mandatory qualifications, experience, ang or skills required to perform the work.		
Applicable personal protective equipment is selected on the SWMS.		
Reflects and documents any legislative references and/or Australian Standards.		
Identifies any hazardous substances used with specific control measures in line with any SDS.	\boxtimes	
REVIEWED BY	DATE REVIEW	ED .
SIGNATURE	DATE COMPLET	ED

Version 2.5 Authorised by Review # Date of Issue: Review Date: 21